



# Centrifuge 5910 Ri

**Original instructions** 

Copyright © 2020 Eppendorf AG, Germany. All rights reserved, including graphics and images. No part of this publication may be reproduced without the prior permission of the copyright owner.

Corning® is a registered trademark of Corning Inc., USA.

Microtainer® is a registered trademark of Becton Dickinson, USA.

Parasep® is a registered trademark of Apacor Ltd, UK.

Eppendorf® and the Eppendorf Brand Design are registered trademarks of Eppendorf AG, Germany.

Eppendorf QuickLock®, Eppendorf VisioNize ® and FastTemp pro® are registered trademarks of Eppendorf AG, Germany.

FastTemp™ is a protected trademark of Eppendorf AG, Germany.

Registered trademarks and protected trademarks are not marked in all cases with ® or TM in this manual.

U.S. Design Patents are listed on www.eppendorf.com/ip

# **Table of contents**

1	Oper	ating ins	structions	9
	1.1	Using t	this manual	9
	1.2	Danger	r symbols and danger levels	9
		1.2.1	Danger symbols	9
		1.2.2	Danger levels	9
	1.3	Symbo	Is used	10
	1.4	Abbrev	viations used	10
2	Cata			11
2	2.1	-	ed use	
	2.1			
	2.2		rofile	
			ation on product liability	
	2.4		ation limits	
	2.5	2.4.1	· · · · · · · · · · · · · · · · · · ·	
	2.5		ngs for intended use	
		2.5.1	Personal injury or damage to the device	
		2.5.2	Incorrect handling of the centrifuge	
		2.5.3	Incorrect handling of the rotors	
	o (	2.5.4	Extreme strain on the centrifugation tubes	
	2.6	Safety	instructions on the device and accessories	17
3	Prod	uct desc	ription	19
	3.1	Produc	et overview	19
	3.2	Deliver	y package	20
	3.3	Feature	es	20
	3.4	Name p	plate	21
4	Insta	llation		23
-	4.1		ng the location	
	4.2		ing installation	
	4.2		ng the instrument	
	4.3	4.3.1	Connecting the device to the mains/power line	
	4.4		ering the device	
	4.4	4.4.1	VisioNize onboard devices	
		4.4.1		
		4.4.2	Registering for VisioNize	
5	Oper			
	5.1	Initial s	steps	
		5.1.1	Setting up the device	
	5.2	Switch	ing the device on and off	
		5.2.1	Switching on the device	
		5.2.2	Switching off the device	29
	5.3	Openin	ng and closing the centrifuge lid	29
	5.4	Replac	ing the rotor	30
		5.4.1	Inserting the rotor	30
		5.4.2	Removing the rotor	30
		5.4.3	Triggering rotor detection	31

	5.5	Loading	g a fixed-angle rotor	. 31
		5.5.1	Closing the rotor lid	. 32
		5.5.2	Closing the QuickLock rotor lid	. 32
	5.6	Loading	g a swing-bucket rotor	. 32
		5.6.1	Inserting the bucket in the swing-bucket rotor	. 33
		5.6.2	Performing an imbalance calibration	. 34
		5.6.3	Loading buckets symmetrically	. 34
		5.6.4	Closing the bucket with the cap	. 36
		5.6.5	Mixed equipping with different buckets	. 36
	5.7	Informa	tion on aerosol-tight centrifugation	. 37
		5.7.1	Aerosol-tight centrifugation in a fixed-angle rotor	. 37
	5.8	Operation	ng the user interface	. 38
		5.8.1	Home screen	. 39
		5.8.2	Logging in and out as a user	. 40
		5.8.3	Symbols	. 41
	5.9	Menu.	· · · · · · · · · · · · · · · · · · ·	. 41
		5.9.1	Opening the menu	. 41
		5.9.2	Events	. 42
		5.9.3	Run Records	. 43
		5.9.4	Export	. 45
		5.9.5	Locking and cleaning the touchscreen	. 45
6	Centr	ifugation	1	. 47
	6.1	Centrifu	ugation with time setting	. 47
		6.1.1	Setting the centrifugation time	. 47
		6.1.2	Setting the temperature	. 48
		6.1.3	Setting the rotational speed or g-force	. 49
		6.1.4	Setting the acceleration ramp and braking ramp	. 50
		6.1.5	Starting centrifugation	. 50
		6.1.6	End of centrifugation	. 51
	6.2	Starting	centrifugation with the Short Spin function	. 52
		6.2.1	Making Short Spin settings	. 52
		6.2.2	Starting and stopping Short Spin centrifugation	. 52
	6.3	Starting	a temperature control run with the FastTemp function	. 53
		6.3.1	Making FastTemp settings	. 53
		6.3.2	Performing a temperature control run	. 53
7	User	administ	tration	. 55
	7.1	The use	er management concept	. 55
		7.1.1	Administrator	. 55
		7.1.2	User with standard rights	. 55
		7.1.3	User with restricted rights	. 55
		7.1.4	User rights without user management	. 55
		7.1.5	User rights	. 55
	7.2	Setting	up user management	
		7.2.1	Creating an administrator	. 59
		7.2.2	Editing user management	
		7.2.3	Disabling user management	

	7.3	Editing	user accounts as an administrator	62
		7.3.1	Creating a user account	62
		7.3.2	Editing user accounts	63
		7.3.3	Deleting a user account	63
		7.3.4	Resetting the password/PIN for a user account	64
	7.4	Admini	strating your own user account	65
8	Progr	amming		67
	8.1	Favorite	es function	67
		8.1.1	Accessing the Favorites function	67
		8.1.2	Creating a favorite for Time, Temperature and Speed	67
	8.2	Progran	ms function	
		8.2.1	Accessing the Programs function	
		8.2.2	Creating a program	
		8.2.3	Managing programs	
9	Settir	าตร		71
•	9.1	-	ng settings	
	9.2		his Centrifuge 5910 Ri	
	9.3		Settings	
	7.0	9.3.1	Accessing System Settings	
		9.3.2	Accessing Date & Time settings	
		9.3.3	Accessing Network settings	
		9.3.4	Activating Manual Setup	
		9.3.5	Accessing VisioNize Setup	
	9.4		Settings	
	,,,	9.4.1	Accessing Device Settings	
		9.4.2	Display Settings.	
		9.4.3	Language	
		9.4.4	Short Spin	
		9.4.5	Sound Settings	
	9.5		service intervals	
		9.5.1	Accessing Maintenance & Qualification	
		9.5.2	Adding Recurring Tasks	
		9.5.3	Rotor Health	
10	Main	tenance		77
	10.1	Service		77
		10.1.1	Confirming Recurring Tasks	
		10.1.2	Displaying Rotor Health	
	10.2		ng cleaning/disinfection	
	10.3	•	ning cleaning/disinfection	
		10.3.1	Cleaning and disinfecting the device	
		10.3.2	Cleaning and disinfecting the rotor	
		10.3.3	Changing the seal of the aerosol-tight cap	
	10.4		nal care instructions for refrigerated centrifuges	
	10.5		g glass breakage	
	10.6		ng the excess current switch	
	10.7		amination before shipment	
	10.8		ning a software update	

11	Troub	leshooting	1
	11.1	General errors	7
		11.1.1 Restarting the software	7
		11.1.2 Checking the cable connections	7
	11.2	Emergency release	3
12	Trans	port, storage and disposal	•
	12.1	Transport	)
	12.2	Storage	)
	12.3	Disposal	)
13	Techn	iical data91	
	13.1	Power supply91	l
	13.2	Weight/dimensions	l
	13.3	Noise level	
	13.4	Ambient conditions	2
	13.5	Application parameters92	2
	13.6	Temperatures	2
	13.7	Acceleration and deceleration times93	3
	13.8	Service life of accessories	5
14	Rotor	s for the Centrifuge 5910 Ri	
	14.1	Rotor S-4×Universal	
		14.1.1 Swing-bucket rotor S-4xUniversal with 4 universal buckets	7
		14.1.2 Swing-bucket rotor S-4xUniversal with 4 universal buckets and a plate carrier 100	)
	14.2	Rotor S-4×750	2
		14.2.1 Swing-bucket rotor S-4x750 with 4 750 mL round buckets	2
		14.2.2 Swing-bucket rotor S-4x750 with 4 plate buckets	ć
	14.3	Rotor S-4×500	3
		14.3.1 Swing-bucket rotor S-4x500 with 4 500 mL rectangular buckets	3
		14.3.2 Swing-bucket rotor S-4x500 with 4 MTP/Flex buckets	3
	14.4	Rotor S-4×400	)
	14.5	Rotor FA-6×50	<u>)</u>
	14.6	Rotor FA-20x5	1
	14.7	Rotor FA-48×2	5
	14.8	Rotor FA-30×2	7
	14.9	Rotor FA-6x250	3
	1// 10	Rotor F-/48×15	

15	Order	ing infor	mation	123
	15.1	Rotors a	nd accessories	123
			Rotor S-4×Universal	
		15.1.2	Rotor S-4×750	124
		15.1.3	Rotor S-4×500	125
		15.1.4	Rotor S-4×400	125
		15.1.5	Rotor FA-6×50	125
		15.1.6	Rotor FA-20×5	126
		15.1.7	Rotor FA-48×2	126
		15.1.8	Rotor FA-30×2	126
		15.1.9	Rotor F-48×15	127
		15.1.10	Rotor FA-6x250	127
	15.2	Accesso	ries	127
	Certif	icates		129

**Table of contents** Centrifuge 5910 Ri English (EN)

8

# 1 Operating instructions

# 1.1 Using this manual

- ▶ Read this operating manual completely before using the device for the first time. Observe the instructions for use of the accessories where applicable.
- ▶ This operating manual is part of the product. Please keep it in a place that is easily accessible.
- ▶ Enclose this operating manual when transferring the device to third parties.
- ► The current version of the operating manual for all available languages can be found on our webpage <a href="https://www.eppendorf.com/manuals">www.eppendorf.com/manuals</a>.

# 1.2 Danger symbols and danger levels

# 1.2.1 Danger symbols

The safety instructions in this manual have the following danger symbols and danger levels:

	Biohazard	A	Electric shock
<u></u>	Hazard point	兼	Material damage
	Explosive substances		Risk of crushing

# 1.2.2 Danger levels

DANGER	Will lead to severe injuries or death.
WARNING	May lead to severe injuries or death.
CAUTION	May lead to light to moderate injuries.
NOTICE	May lead to material damage.

# 1.3 Symbols used

Depiction	Meaning
1.	Actions in the specified order
2.	
•	Actions without a specified order
•	List
Text	Display or software texts
•	Additional information

# 1.4 Abbreviations used

## MTP

Microplate

#### PCR

Polymerase Chain Reaction

## rcf

Relative centrifugal force : g-force in m/s<sup>2</sup>

# rpm

Revolutions per minute

## UV

Ultraviolet radiation

# 2 Safety

#### 2.1 Intended use

The Centrifuge 5910 Ri is used for the separation of aqueous solutions and suspensions of different densities in approved sample tubes.

The Centrifuge 5910 Ri is exclusively intended for use indoors. All country-specific safety requirements for operating electrical equipment in the laboratory must be observed.

# 2.2 User profile

The device and accessories may only be operated by trained and skilled personnel.

Before using the device, read the operating manual and the instructions for use of the accessories carefully and familiarize yourself with the device's mode of operation.

# 2.3 Information on product liability

In the following cases, the designated protection of the device may be affected. The liability for any resulting damage or personal injury is then transferred to the owner:

- The device is not used in accordance with the operating manual.
- The device is used outside of its intended use.
- The device is used with accessories or consumables that are not recommended by Eppendorf.
- The device is maintained or repaired by persons not authorized by Eppendorf AG.
- The user makes unauthorized changes to the device.

# 2.4 Application limits

## 2.4.1 Declaration concerning the ATEX directive (2014/34/EU)



#### DANGER! Risk of explosion.

- ▶ Do not operate the device in areas where work with explosive substances is carried out.
- ▶ Do not use this device to process any explosive or highly reactive substances.
- ▶ Do not use this device to process any substances which may generate an explosive atmosphere.

Due to its design and the environmental conditions inside the device, the Centrifuge 5910 Ri is not suitable for use in a potentially explosive atmosphere.

The device may only be used in a safe environment, such as in the open environment of a ventilated laboratory or a fume hood. The use of substances that may contribute to a potentially explosive atmosphere is not permitted. The final decision on the risks associated with the use of such substances lies with the user.

## 2.5 Warnings for intended use

## 2.5.1 Personal injury or damage to the device



# WARNING! Risk of electric shock due to damage to the device or to the mains/power cord.

- ▶ Only switch on the device if the device and the mains/power cord are undamaged.
- Only operate devices which have been installed or repaired properly.
- ▶ In the event of danger, disconnect the device from the mains/power supply voltage. Disconnect the mains/power plug from the device or the earth/grounded socket. Use the isolating device intended for this purpose (e.g., the emergency switch in the laboratory).



#### WARNING! Lethal voltages inside the device.

If you touch any parts which are under high voltage you may experience an electric shock. Electric shocks cause heart injury and respiratory paralysis.

- Ensure that the housing is closed and undamaged.
- ▶ Do not remove the housing.
- ▶ Ensure that no liquids can penetrate the device.

Only authorized service staff may open the device.



#### WARNING! Risk due to incorrect voltage supply.

- ▶ Only connect the device to voltage sources which correspond with the electrical requirements on the name plate.
- ▶ Only use earth/grounded sockets with a protective earth (PE) conductor.
- ▶ Only use the mains/power cord supplied.



#### WARNING! Damage to health due to infectious liquids and pathogenic germs.

- ▶ When handling infectious liquids and pathogenic germs, observe the national regulations, the biosafety level of your laboratory, and the manufacturers' Safety Data Sheets and application notes.
- Use aerosol-tight locking systems to centrifuge these substances.
- ▶ When working with pathogenic germs which belong to a higher risk group, use more than one aerosol-tight bioseal.
- ▶ Wear your personal protective equipment.
- ► For comprehensive regulations about handling germs or biological material of risk group II or higher, please refer to the "Laboratory Biosafety Manual" (source: World Health Organization, Laboratory Biosafety Manual, in the currently valid version).



#### WARNING! Risk of injury from rotating rotor.

If the emergency release of the lid is activated, the rotor may continue to rotate for several minutes.

- ▶ Wait for the rotor to stop before activating the emergency release.
- ▶ To check, look through the monitoring glass in the centrifuge lid.



#### WARNING! Risk of injury due to defective gas spring(s).

A defective gas spring is an insufficient support for the centrifuge lid. There is a risk of crushing fingers or limbs.

- ▶ Ensure that the centrifuge lid can be opened completely and that it remains in this position.
- ▶ Regularly check all gas springs for their proper function.
- ▶ Have defective gas springs replaced immediately.
- ▶ Have gas springs replaced by a service technician every 2 years.



#### WARNING! Risk of injury from chemically or mechanically damaged accessories.

Even minor scratches and cracks can lead to severe internal material damage.

- ▶ Protect all accessory parts from mechanical damage.
- ▶ Inspect the accessories for damage before each use. Replace any damaged accessories.
- ▶ Do not use accessories that have exceeded their maximum service life.



## **CAUTION!** Risk of poor safety due to incorrect accessories and spare parts

The use of accessories and spare parts other than those recommended by Eppendorf may impair the safety, functioning and precision of the device. Eppendorf cannot be held liable or accept any liability for damage resulting from the use of accessories and spare parts other than those recommended or from improper use.

▶ Only use accessories and original spare parts recommended by Eppendorf.



#### NOTICE! Damage to the device due to spilled liquids.

- 1. Switch off the device.
- 2. Disconnect the device from the mains/power supply.
- 3. Carefully clean the device and the accessories in accordance with the cleaning and disinfection instructions in the operating manual.
- 4. If a different cleaning and disinfecting method is to be used, contact Eppendorf AG to ensure that the intended method will not damage the device.



#### NOTICE! Damage to electronic components due to condensation.

Condensate may form in the device when it has been transported from a cool environment to a warmer environment.

▶ After installing the device, wait for at least 4 h. Only then connect the device to the mains/ power line.



#### NOTICE! Centrifuge 5910 Ri: Compressor damage after improper transport.

▶ Wait 4 hours before switching on the centrifuge after setting it up.

# 2.5.2 Incorrect handling of the centrifuge



### NOTICE! Damage from knocking against or moving the device during operation.

If the rotor hits against the rotor chamber wall, this will cause considerable damage to the device and rotor.

▶ Do not move or knock against the device during operation.

#### 2.5.3 Incorrect handling of the rotors



#### WARNING! Risk of injury from improperly attached rotors and rotor lids.

- ▶ Only centrifuge with the rotor and rotor lid firmly tightened.
- ▶ If unusual noises occur when the centrifuge starts, the rotor or the rotor lid may not be attached properly. Stop the centrifugation immediately.



#### CAUTION! Risk of injury due to asymmetric loading of a rotor.

- ▶ Always load all positions of a swing-bucket rotor with buckets.
- ▶ Load buckets symmetrically with identical tubes or plates.
- ▶ Only load adapters with suitable tubes or plates.
- ▶ Always use tubes or plates of the same type (weight, material/density and volume).
- ▶ Check that loading is symmetrical by balancing the adapters and tubes or plates used with a balance.



### CAUTION! Risk of injury from overloaded rotor.

The centrifuge is designed for the centrifugation of material with a maximum density of 1.2 g/mL at maximum speed and filling volume and/or load.

Do not exceed the maximum load of the rotor.



#### CAUTION! Risk of injury due to chemically damaged rotor lids or caps.

Transparent rotor lids or caps made of PC, PP or PEI may lose their strength if exposed to organic solvents (e.g., phenol, chloroform).

- ▶ If rotor lids or caps have come into contact with organic solvents, clean them immediately.
- ▶ Regularly check the rotor lids and caps for damage and cracks.
- ▶ Immediately replace rotor lids or caps that show cracks or milky stains.



#### NOTICE! Damage to rotors from aggressive chemicals.

Rotors are high-quality components which withstand extreme stresses. This stability can be impaired by aggressive chemicals.

- ▶ Avoid using aggressive chemicals such as strong and weak alkalis, strong acids, solutions with mercury ions, copper ions and other heavy metal ions, halogenated hydrocarbons, concentrated saline solutions and phenol.
- ▶ If it is contaminated by aggressive chemicals, clean the rotor and especially the rotor bores immediately using a neutral cleaning agent.
- ▶ Due to the manufacturing process, color variations may occur on PTFE coated rotors. These color variations do not affect the service life or resistance to chemicals.



## NOTICE! If handled incorrectly, the rotor may fall.

The swing-bucket rotor may fall if the buckets are used as handles.

- ▶ Remove the buckets before inserting and/or removing a swing-bucket rotor.
- ▶ Always use both hands to carry the rotor cross.



#### NOTICE! If handled incorrectly, the rotor may fall.

- ▶ Always grasp the F-48x15 rotor with both hands.
- In order to hold the rotor safely, you may have to remove 3 to 4 opposing sleeves from the outer row.



#### NOTICE! Buckets swinging out in the wrong direction.

If the wrong adapters are used for 500 mL Corning flasks, the buckets of the swing-bucket rotor may swing out in the wrong direction. If the buckets swing out in the wrong direction, this may lead to sample loss or damage to the centrifuge.

▶ Therefore, only use the Eppendorf adapters for 500 mL Corning flasks intended for this purpose.

### 2.5.4 Extreme strain on the centrifugation tubes



#### CAUTION! Risk of injury from overloaded tubes.

- ▶ Note the loading limits specified by the tube manufacturer.
- ▶ Only use tubes which are approved by the manufacturer for the required *g*-forces (rcf).



#### NOTICE! Risk from damaged tubes.

Damaged tubes must not be used as this could cause further damage to the device and the accessories and loss of the samples.

Visually check all tubes for damage before use.



# NOTICE! Danger due to deformed or brittle tubes. Autoclaving at excessive temperatures can lead to plastic tubes becoming brittle and deformed.

This could cause damage to the device and the accessories and sample loss.

- ▶ Observe the temperatures specified by the manufacturer when autoclaving tubes.
- ▶ Do not use deformed or brittle tubes.



#### **NOTICE!** Danger due to open tube lids.

Open tube lids may break off during centrifugation and damage both the rotor and the centrifuge.

Carefully seal all tube lids before centrifuging.



#### NOTICE! Damage to plastic tubes due to organic solvents.

When using organic solvents (e.g., phenol, chloroform), the strength of plastic tubes may be reduced and the tubes may become damaged.

▶ Observe the manufacturer's information on the chemical resistance of the tubes.

# 2.6 Safety instructions on the device and accessories

Symbol	Meaning	Location
	NOTICE  ➤ Observe the safety instructions in the operating manual.	Right side of the device
<b>i</b>	▶ Observe the operating manual.	Right side of the device
	<ul> <li>Always load all 4 positions of the swing-bucket rotor with buckets.</li> <li>Always tighten the rotor with the enclosed rotor key.</li> </ul>	Inside of the centrifuge lid
	Warning of biological risks when handling infectious liquids or pathogenic germs.	Aerosol-tight fixed-angle rotors: rotor lid Aerosol-tight buckets: cap

Safety Centrifuge 5910 Ri English (EN)

18

# 3 Product description

# 3.1 Product overview




Fig. 3-1: Centrifuge 5910 Ri: Front and side view

- 1 Centrifuge lid
- 2 Monitoring glass
  Visual monitoring for rotor stop

Visual monitoring for rotor stop or speed control option using stroboscope.

- 3 Touchscreen
- 4 Emergency release
- 5 Ethernet port

- 6 Name plate
- 7 USB interface (type B)
- 8 Mains/power cord socket
  Connection for the mains/power cord supplied.
- 9 Mains/power switch Switch for switching the centrifuge on and off.
- 10 USB interface (type A)

# 3.2 Delivery package

1	Centrifuge 5910 Ri
1	Rotor key
1	Mains/power cord
1	Directions



- ▶ Check that the delivery is complete.
- ▶ Check all parts for transport damage.
- ▶ To safely transport and store the device, retain the transport box and packing material.

#### 3.3 Features

The versatile Centrifuge 5910 Ri has a capacity of up to  $4 \times 1000$  mL and achieves a maximum of  $22132 \times g$  or 14000 rpm. You can choose from a range of rotors to centrifuge the following tubes for your various applications:

- Micro test tubes (0.2 mL to 5.0 mL)
- Microtainers
- · Spin columns
- · Cryogenic tubes
- Conical tubes (15 mL, 50 mL)
- Bottles (175 mL to 1000 mL)
- Microplates
- PCR plates
- · Deepwell plates
- Slides (with CombiSlide adapter)
- · Blood collection systems

Handling the centrifuge is facilitated by:

- Automatic rotor detection with rotational speed limit
- Automatic rotor imbalance detection
- Touchscreen for operating the centrifuge software

The centrifuge has a favorites function and allows individual programs to be created and managed.

The possibility of setting the radius manually ensures maximum rcf accuracy.

The Centrifuge 5910 Ri also features a temperature control function for centrifuging at temperatures from -11 °C to 40 °C. Use the **FastTemp** function to start a temperature control run without samples, to adjust the rotor chamber including the rotor, buckets and adapters quickly to the set temperature. Continuous cooling also maintains the temperature in the rotor chamber with the centrifuge lid closed when the centrifuge is not in use.

# 3.4 Name plate




Fig. 3-2: Eppendorf AG device identification (example)

- 1 Maximum density of the material for centrifuging
- 2 Maximum kinetic energy
- 3 Maximum speed
- 4 Serial number
- 5 Product name
- 6 Rated voltage
- 7 Rated frequency
- 8 Maximum rated current

- 9 Maximum rated power
- 10 Information on the refrigerant (refrigerated centrifuges only)
- 11 Data matrix code for serial number
- 12 Designation of origin
- 13 CE marking
- 14 Certification marks and symbols (device-specific)
- 15 Manufacturer's address
- 16 Manufacturer

Tab. 3-1: Certification and conformity marks and symbols (device-specific)

Symbol/sign	Meaning		
SN	Serial number		
	Manufacturer's name and address		
IVD	Identification mark for an in vitro diagnostic medical device in accordance with directive 98/79/EC of the European Union		
	Marking of electrical and electronic equipment in conformity with standard EN 50419 in accordance with directive 2012/19/EU (WEEE) of the European Union		
C UL US LISTED	UL listing certification mark: Representative samples of the device have been tested by Underwriters Laboratories (UL) in accordance with the applicable safety standards for the USA and Canada		
FC	FCC mark of conformity; the instrument's electromagnetic compatibility has been tested in accordance with <i>Federal Communications Commission</i> (FCC, USA) regulations		
<b>©</b>	RoHS mark in accordance with standard SJ/T 11364, Marking for the restriction of the use of hazardous substances in electrical and electronic products, People's Republic of China		
EAL	EAC marking for medical devices; conformity with the technical regulations of the Eurasian Economic Union		
EAC	Conformity with the relevant directives for the Eurasian Economic Union		

#### 4 Installation

# 4.1 Selecting the location



#### WARNING! Risk of fire.

A high current consumption of the centrifuge can lead to an overload in unprotected mains/power lines.

- ▶ Only connect the centrifuge to an electric circuit that has its own protection.
- ▶ Do not connect any devices to the circuit other than the centrifuge.
- ▶ Only use the mains/power cord supplied.



# NOTICE! If an error occurs, objects in the immediate vicinity of the device may become damaged.

- ► In accordance with the recommendations of EN 61010-2-020, leave a safety clearance of **30 cm** around the device during operation.
- ▶ Please remove all materials and objects from this area.



#### NOTICE! Risk of damage due to overheating.

- ▶ Do not install the device near heat sources (e.g., heaters, drying cabinets).
- ▶ Do not expose the device to direct sunlight.
- ▶ Ensure unobstructed air circulation. Maintain a clearance of at least 30 cm around all ventilation gaps.



#### **NOTICE!** Radio interference.

For devices with Class A noise emission in accordance with EN 61326-1/EN 55011, the following applies: This device has been developed and tested in accordance with CISPR 11 Class A. The device may cause radio interference in domestic environments and is not intended for use in residential areas. The device cannot ensure adequate protection of radio reception in residential areas and domestic environments.

▶ If necessary, take appropriate measure to eliminate the interferences.



Mains/power connection for centrifuges: Operation of the centrifuge is only permitted in building installations that comply with the applicable national regulations and standards. In particular, it must be ensured that there are no impermissible loads on the supply lines and assemblies that are located upstream of the internal protection of the device. This can be ensured by additional circuit breakers or other suitable safety elements in the building installation.



The mains/power switch and the disconnecting device of the mains/power line must be easily accessible during operation (e.g., a residual current circuit breaker).

Select the location of the device according to the following criteria:

- Mains/power connection in accordance with the name plate.
- Minimum distance to other devices and walls: 30 cm.
- A resonance-free bench with a horizontal and even work surface which is designed to support the weight of the device.
- The surrounding area must be well ventilated.
- The location is protected against direct sunlight.
- ▶ Do not use this device near strong electromagnetic sources (e.g., unshielded high frequency sources) as they could impede proper functioning of the device.

# 4.2 Preparing installation

The weight of the centrifuge is 109 kg.



#### CAUTION! Risk of injury when lifting and carrying heavy loads

▶ Use a lifting aid to install the device.

#### Unpacking the centrifuge

- 1. Loosen the straps.
- 2. Lift the carton upward and remove it.
- 3. Remove accessories.
- 4. Remove the transport securing devices.
- 5. Remove the plastic sleeve.
- 6. Lift the centrifuge using a suitable mechanical lifting aid.
- 7. Place the device on a suitable lab bench.

## 4.3 Installing the instrument

## 4.3.1 Connecting the device to the mains/power line

Prerequisites

The device is on a suitable lab bench.



# WARNING! Risk due to incorrect voltage supply.

- ▶ Only connect the device to voltage sources which correspond with the electrical requirements on the name plate.
- ▶ Only use earth/grounded sockets with a protective earth (PE) conductor.
- ▶ Only use the mains/power cord supplied.



#### NOTICE! Damage to electronic components due to condensation.

Condensate may form in the device when it has been transported from a cool environment to a warmer environment.

After installing the device, wait for at least 4 h. Only then connect the device to the mains/ power line.



## NOTICE! Compressor damage after improper transport.

▶ After installation, wait 4 h before switching on the centrifuge.



#### NOTICE! Impairment to the display caused by the protective foil

The display functionality can be impaired if the protective foil is peeled off when the device is switched on.

- ▶ Remove the protective foil before switching on the device for the first time.
- 1. Let the device warm up to ambient temperature.
- 2. Connect the mains connection socket to the power socket using a power cable.
- 3. Remove the protective foil from the touchscreen.
- 4. Switch on the device using the power switch at the back.

The software starts.

# 4.4 Registering the device

To register a VisioNize onboard device for VisioNize Services, a connection to the local network with Internet access is required. If the device is connected to the Internet, it can be logged into VisioNize via the administrator account access data. Information on VisioNize can be found in the manual at <a href="https://www.eppendorf.com/visionize-software-manual">https://www.eppendorf.com/visionize-software-manual</a>.

#### 4.4.1 VisioNize onboard devices

#### **Prerequisites:**

- Available Ethernet port near the device
- · Standard Ethernet cable
- Internet access
   Administrator account (Tenant) for VisioNize



Prevention of data loss, loss of samples or misuse of data

▶ Protect the VisioNize onboard device from unauthorized access via the internet. Contact IT systems administration for questions.



Security risks

▶ Only enable OPC/REST when required. Every communication protocol used to transmit data via the Internet represents a potential security risk.

#### Connecting to the network



- 1. Connect the Ethernet port of the device to the local network with a standard Ethernet cable via an available Ethernet port.
- 2. To check the network connection, tap the *Settings* button.
- 3. Tap on Menu > Settings > System Settings > Network.

#### **DHCP**




- 4. The device can be easily integrated into the network using the DHCP network protocol. Enable the *Enable DHCP* slider.
- 5. If no DHCP is in use, disable Enable DHCP.
- 6. Tap the Manual Setup button.
- 7. Enter the device parameters for the network.
- 8. To check the entries: Call Menu > Settings > System Settings > Network.

When the device has been integrated into the network, the IP address of the device will appear next to *IP Addresses*.


If the IP address is not displayed, note the MAC address and contact IT systems administration.

# 4.4.2 Registering for VisioNize

VisioNize onboard devices require a certificate for VisioNize. After the device has been put into operation and connected to the local network, the registration dialog will start automatically.




1. To configure the device for VisioNize, tap the *Continue* > button and follow the instructions.




2. Enter a name for the device.


The device is identified in the network with this name.



3. Select the time zone for the device in the drop-down list and tap on *Continue* >.



To link the device directly to the VisioNize account, tap the *Connect* button.
 To connect the device to the cloud at a later time, tap on *Connect Later*.



- 5. Enter the administrator account's login data for VisioNize.
- 6. Press *Confirm* to confirm.



7. Check the registration for VisioNize.

The device is registered under VisioNize in the cloud.

If the device is registered in the cloud, a cloud is displayed in the status bar. Additionally, the *VisioNize Setup (connected)* menu item under *System Settings* is displayed in gray.

# 5 Operation

# 5.1 Initial steps

Before the Centrifuge 5910 Ri is used for the first time, the following points must be met:

- The device is correctly connected.
- The device is free of damage.
- Unobstructed air circulation at the ventilation gaps is ensured.

## 5.1.1 Setting up the device

1. Switch on the device at the mains/power switch on the right side of the device.

At this point the software starts in English and guides the user through the *Setup*.



After *Setup* has been completed, the user interface language can be changed under *Menu>Settings>Device Settings>Language*.

# 5.2 Switching the device on and off

## 5.2.1 Switching on the device

- 1. Switch on the device at the mains/power switch on the right side of the device.
  - · The software starts.
  - The device is ready for operation after 90 seconds.

## 5.2.2 Switching off the device

1. Press the *Open* button.

Residual moisture can evaporate. The pressure on the gas springs is released.

- 2. Remove the rotor lids from the fixed-angle rotors and the aerosol-tight caps from the buckets. Aerosol-tight accessories may not be stored when they are closed.
- 3. Switch off the centrifuge using the mains/power switch.

# 5.3 Opening and closing the centrifuge lid

- ▶ Press the *Open* button to open the locked centrifuge lid.
  - The electronic lid latch is unlocked and the centrifuge lid is automatically lifted slightly.
- ▶ Manually push the centrifuge lid up completely.
  - Shock absorbers hold the centrifuge lid in the open position.
- ▶ To close the centrifuge lid, press the centrifuge lid down manually until the electronic lid latch engages and locks the centrifuge lid.

# 5.4 Replacing the rotor



#### NOTICE! If handled incorrectly, the rotor may fall.

The swing-bucket rotor may fall if the buckets are used as handles.

- ▶ Remove the buckets before inserting and/or removing a swing-bucket rotor.
- ▶ Always use both hands to carry the rotor cross.




#### NOTICE! Material damage due to improper rotor insertion.

The motor shaft or bearing may become damaged if the rotor falls into the motor shaft guides in an uncontrolled manner when it is inserted.

- ▶ Hold the rotor with both hands.
- Guide the rotor onto the motor shaft.

## 5.4.1 Inserting the rotor



- 1. Place the rotor vertically onto the motor shaft from the top.
  - The arrows on the rotor show the position of the pegs. The pegs of the rotor must fit into the guides of the motor shaft. If required, lift the rotor and place it onto the motor shaft again.
- 2. Insert the supplied rotor key into the rotor nut.
- 3. Turn the rotor key clockwise until the rotor nut is firmly tightened.

# 5.4.2 Removing the rotor

- 1. Turn the rotor nut counterclockwise with the rotor key included in the delivery.
- 2. Lift the rotor out vertically.

# 5.4.3 Triggering rotor detection



#### CAUTION! Risk of injury when turning the rotor manually.

- ▶ When turning a swing-bucket rotor, pay special attention to ensure that your fingers do not get jammed or get caught on the swinging buckets.
- ▶ Manually turn the rotor counterclockwise to trigger rotor detection.
- The display briefly shows the message *Rotor detected:* with the rotor designation which is located in the device.
- After the message on the display goes out, the rotor designation appears in the status bar.



After a rotor change, the automatic radius is adjusted and the rcf value changes.

# 5.5 Loading a fixed-angle rotor



#### CAUTION! Risk of injury due to asymmetric loading of a rotor.

- ▶ Load rotors symmetrically with identical tubes.
- ▶ Only load adapters with suitable tubes.
- ▶ Always use the same type of tubes (weight, material/density and volume).
- ▶ Check that loading is symmetrical by balancing the adapters and tubes used with a balance.
- 1. Check the maximum payload (adapter, tube and contents) for each rotor bore.
- 2. Load rotors and adapters only with the tubes intended for them.
- 3. To ensure symmetrical loading, insert sets of two tubes in opposite bores. Tubes located opposite each other must be of the same type and contain the same filling quantity.




Fig. 5-1: Symmetrical loading of a fixed-angle rotor

To minimize weight differences between filled sample tubes, we recommend balancing with a balance. This will reduce wear on the drive and reduce operating noise.


# 5.5.1 Closing the rotor lid



#### Use matching rotor lids

- Fixed-angle rotors may only be operated with the appropriate rotor lid in each case. The rotor name on the rotor must correspond to the rotor name on the rotor lid.
- 1. Place the rotor lid vertically on the rotor.
- 2. Turn the rotor lid screw clockwise to seal the rotor.

# 5.5.2 Closing the QuickLock rotor lid



- 1. Check the correct positioning of the external sealing ring in the groove.
- 2. Place the rotor lid on the rotor in a vertical motion.
- 3. To lock the rotor, turn the rotor lid screw clockwise as far as it will go, and after an audible "click" is heard.



The rotor is only properly locked after the audible "click"!

# 5.6 Loading a swing-bucket rotor



## CAUTION! Risk of injury due to asymmetric loading of a rotor.

- ▶ Always load all positions of a swing-bucket rotor with buckets.
- ▶ Load buckets symmetrically with identical tubes or plates.
- ▶ Only load adapters with suitable tubes or plates.
- ▶ Always use tubes or plates of the same type (weight, material/density and volume).
- Check that loading is symmetrical by balancing the adapters and tubes or plates used with a balance.



#### NOTICE! Material damage due to incorrect equipping of the swing-bucket rotor.

Incomplete equipping of the swing-bucket rotor or an uneven load will reduce the life span of the rotor and the corresponding buckets considerably.

- ▶ Always load all positions of a swing-bucket rotor with buckets.
- ▶ Load opposite buckets with the same weight (adapter, tubes, or plates and content).




Fig. 5-2: Swing-bucket rotors: Loading all positions with buckets

# 5.6.1 Inserting the bucket in the swing-bucket rotor

#### **Prerequisites**

- The combination of rotor, bucket and adapter has been approved by Eppendorf.
- Buckets that are located opposite each other belong to the same weight class. The weight class is engraved in the sides of the groove: e.g., 68.
- · Matching and tested tubes and plates.



The swing-bucket rotor runs more smoothly if all buckets are loaded symmetrically and with the same weight.

- ▶ To reduce noise and vibrations, load the buckets of the swing-bucket rotor with the same weight.
- 1. Check that the bucket grooves are clean. Use pivot grease to lightly lubricate the grooves.
- 2. Hang the buckets into the rotor.
  - All rotor positions must be equipped with buckets.
- 3. Check to see if all buckets are completely hung and can freely swing out.
- 4. Check the maximum load per bucket (adapter, vessel or plate and contents) and the loading height.
- 5. Load the buckets symmetrically.



▶ When using a vessel type or plate type for the first time, carry out a brief test run at low speed (e.g., 1000 rpm).

# 5.6.2 Performing an imbalance calibration

Carry out a manual imbalance calibration when you use a tube or plate for the first time. Always carry out a manual imbalance calibration when you use tubes with a length of > 100 mm.

- ▶ Inserting plates and/or tubes.
- ▶ Swing the buckets manually up to 90°.
  - · Bucket swings freely.
  - The tubes do not touch the rotor cross.

## 5.6.3 Loading buckets symmetrically

# 5.6.3.1 Equipping buckets with vessels




Fig. 5-3: Swing-bucket rotors: Incomplete, but symmetric loading of the buckets.

The loading shown on the right-hand side is incorrect as it places an uneven load on the pegs of the rotor.

▶ To reduce vibrations and noise, load all buckets of the swing-buckets rotor equally.

## 5.6.3.2 Loading plates symmetrically



#### NOTICE! Filling the plates too high can cause overflowing.

During the run the meniscuses in the tubes along the edges of the plates are at an angle. This is due to the centrifugal forces and cannot be avoided.

Fill the plate wells to a maximum of 2/3 of the maximum filling volume.




Fig. 5-4: Swing-bucket rotors: Symmetrical loading of plates

▶ In order to avoid imbalances, always load the plates symmetrically.

The plate loading shown on the right-hand side is incorrect as the plate buckets will not swing properly if loaded in this way.

## 5.6.3.3 Rotor S-4×750: Equipping the adapter with vessels > 119 mm




#### NOTICE! Broken glass due to incorrect loading.

If the tubes in a bucket are too long, the swinging tubes will touch the rotor cross and may get damaged or destroyed.

- ▶ Equip buckets of swing-bucket rotors in such a way that they can swing out freely.
- ▶ If necessary, load only the inner bores of the adapter.
- ▶ If using tubes longer than 100 mm: always perform a manual swing-out test.

If the adapter  $16 \times 75$  mm – 100 mm (order number 5825 736.001) is equipped with vessels > 119 mm, e.g., BD 8 mL Vacutainer, this will result in danger of glass breakage.



• Only equip the inner bores.


# 5.6.4 Closing the bucket with the cap



#### NOTICE! Damage to the cap hook.

If the cap is not fitted correctly on the bucket, the sealing clamp may break during closing.

▶ Before you fold the sealing clamp, check that the cap is positioned correctly.



- 1. Fold the cap clamp to the **open** position (1).
- 2. Place the cap on the bucket and push the cap down in such a way that the clamp is lifted slightly (2).
- 3. To transport the bucket, fold the clamp to the carrying position (3).
- 4. To seal the bucket so that it is aerosol-tight, fold the clamp beyond the latch into the **close** position.

The clamp has only been folded correctly if there is an audible *click* (4).

# 5.6.5 Mixed equipping with different buckets

Mixed equipping of swing-bucket rotors with different buckets is possible if these are intended for the rotor. Buckets that are located opposite each other must be of the same type.




Fig. 5-5: Mixed equipping of a swing-bucket rotor

# 5.7 Information on aerosol-tight centrifugation



# WARNING! Damage to health due to limited aerosol tightness with an incorrect rotor/rotor lid combination.

Aerosol-tight centrifugation is guaranteed only if the rotors and rotor lids intended for this purpose are used. The designation of aerosol-tight fixed-angle rotors always starts with **FA**. The aerosol-tight rotors and rotor lids of this centrifuge are additionally marked with a red ring on the rotor and a red rotor lid screw.

- ▶ Always use rotors and rotor lids marked aerosol-tight together for aerosol-tight centrifugation. The details specifying in which centrifuge the aerosol-tight rotors and rotor lids may be used can be found on the rotor and on the top of the rotor lid.
- Only use aerosol-tight rotor lids in combination with the rotors that are specified on the rotor lid.
- ▶ Only use aerosol-tight buckets with the corresponding caps.



#### WARNING! Damage to health due to limited aerosol-tightness if used incorrectly.

Mechanical stresses and contamination by chemicals or other aggressive solvents may impair the aerosol tightness of the rotors and rotor lids. Autoclaving at excessive temperatures can lead to plastic vessels, adapters and rotor lids becoming brittle and deformed.

- ▶ Check the integrity of the seals of the aerosol-tight rotor lids or caps before each use.
- ▶ Only use aerosol-tight rotor lids or caps if the seals are undamaged and clean.
- ▶ Do not exceed temperatures of 121 °C or a time of more than 20 min. while autoclaving.
- ▶ After each proper autoclaving process (121 °C, 20 min.), coat the threads of the rotor lid screw with a thin layer of pivot grease (order no. Int. 5810 350.050, North America 022634330).
- ▶ Only the seal of aerosol-tight rotor lids with exchangeable seals (e.g. QuickLock rotor lids) must be replaced after 50 autoclaving cycles.
- ▶ Replace aerosol-tight rotor caps after 50 autoclaving cycles.
- ▶ **Never** store aerosol-tight rotors or buckets closed.




The aerosol tightness of rotors, rotor lids, buckets and caps has been tested and certified according to Annex AA of IEC 61010-2-020.

### 5.7.1 Aerosol-tight centrifugation in a fixed-angle rotor

### To ensure aerosol tightness, the following applies:

- Replace aerosol-tight rotor lids without exchangeable seal and cap after 50 autoclaving cycles.
- Replace the seal of aerosol-tight rotor lids with exchangeable seal (e.g., QuickLock rotor lids) after 50 autoclaving cycles.
- Lightly grease the replaced seal with pivot grease after it is inserted.

# 5.8 Operating the user interface



- If liquid comes into contact with the touchscreen, the functions displayed on the touchscreen may be triggered.
  - ▶ Do not drop any liquids onto the touchscreen.
  - ▶ Do not spill any liquids onto the touchscreen.

### 5.8.1 Home screen




Fig. 5-6: Home screen

1 Status bar Rotor designation

Time

- 2 Current information on the device status.
- 3 Display of saved favorites or available programs.
- 4 Toolbar

Buttons for navigation and operation of the device

5 Device-specific function


The toolbar (4) contains the buttons for navigating within the software. The toolbar is always visible.

- Home: Jump to the home screen.
- Open/Close: Open or close the centrifuge lid.
- FastTemp: Start temperature control run without sample.
- Start/Stop: Start or stop centrifugation.
- ShortSpin: Short run centrifugation
- Standby/Login: Display of standby mode or login if user management has been set up.
- Menu: The menu items for the device are displayed.

### 5.8.2 Logging in and out as a user

### Prerequisites

• User management has been set up.



- 1 Edit box
- 2 Number pad

- 3 Cancel login
- 4 Delete the entry step by step

### Logging in as a user

- 1. Tap the *Login* button on the home screen.
- 2. Enter your user ID or user name.
- 3. Enter your PIN or password.

  If the correct PIN or password was entered, the user is automatically logged in.

### Logging out as a user

### Prerequisites

- User management has been set up.
- 1. Tap the *Logout* button on the home screen.



Alternatively, a user can also log out in the *Menu* with the *Logout* button.

# 5.8.3 Symbols

Symbol	Description
	Status: Function active
0	Status: Function inactive
	Event log
γ	Filter
Û	Data export
•••	Options menu
4	Notice, value range below minimum threshold. Tap to correct the value range.
4	Notice, value range above maximum threshold. Tap to correct the value range.
<b>(X)</b>	Back

# 5.9 Menu

# 5.9.1 Opening the menu



- Tap the *Menu* button.
   The menu items available for the device are displayed.
- 2. Select the menu item.

### **5.9.2** Events




Fig. 5-7: Events window

- 1 List of all notifications and messages
- 2 Confirm open notifications.

3 Filter options

The button is highlighted in blue when messages are filtered.

4 Export list of messages to a USB storage medium.




100000 notifications and messages are saved. If there are more than 100000 entries, the oldest entries are overwritten.

### **Accessing Events**

- 1. Tap the *Menu* button.
- 2. Tap the Events button.

### Filtering the event list



- Tap the button for the filter options.The window with the settings for the filters opens.
  - Filter by priority
  - Filter by time span
  - · Filter by function
  - Filter by message
  - Filter by acknowledgement status

If a filter is enabled, a checkmark appears next to the filter.

To disable all filters, tap the Clear all filters button.

 Close the selection window.
 The filtered notifications and messages are displayed.

### Accessing more information

- Select a notification or message from the event list.
   The window with detailed information appears.
- 2. Navigate between the notifications and messages using the arrow keys.

#### Exporting the event list

- Connect a USB stick and tap the Export button.
   The event list is saved as an Excel table. If the export was successful, the Export successful window appears.
- 2. To complete the process, confirm the message.

#### 5.9.3 Run Records



All centrifugation runs are documented and stored. If there are more than 1000 entries, the oldest entries are overwritten.

#### Accessing Run Records

- 1. Tap the Menu button.
- 2. Tap the Run Records button.



The list of centrifugation runs that have been completed is displayed.

#### Filtering entries

3. Tap the button for the filter options.

The Set Filters window with the following filter options opens:

- Result: filter by result Completed, Completed with warnings or Failed
- From date: filter from a date
- Until date: filter up to a date
- Program number: filter by program number
- Program name: filter by program name
- User: filter by user if user management has been set

In this window, entries are confirmed with the *Confirm* button or reset with the *Reset Filters* button.

4. Assign values to the required filter options and tap on Confirm.

The filtered entries are displayed.

#### **Exporting entries**

5. Connect a USB stick and tap the *Export* button.

The entries are saved in a PDF document. If the export was successful, the *Export successful* window appears.

#### Displaying information on a centrifugation run


6. Tap the desired list entry.



Information on the selected centrifugation run is displayed and can also be exported.


- Result: The result Completed, Completed with warnings or Failed is displayed
- Initial Parameters: The set time, temperature, speed, acceleration and braking ramps are displayed
- Time Span: The start time and end time is displayed
- Events: Display events during the centrifugation run
- System: System information is displayed
- Rotor: The rotor designation is displayed

### 5.9.4 Export




- 1. Tap the *Menu* button.
- Tap the Export button.A selection list for the export appears.
- 3. Connect a USB stick.
- 4. Select the data for the export.
- 5. Tap the *Export* button to export the selected data.
  - The data is saved. If the export was successful, the *Export successful* window appears.
  - The *Run Records (CSV)* data is exported in UTF-8 format.
- 6. To complete the process, confirm the message.

### 5.9.5 Locking and cleaning the touchscreen



Tap the Menu > Clean Screen button.
 The touchscreen is locked for normal usage and can be cleaned.

#### Unlocking the locked touchscreen



2. Tap the corners in the numbered sequence. The touchscreen is unlocked for operation and the previous screen is displayed.

**Operation** Centrifuge 5910 Ri English (EN)

46

# 6 Centrifugation

# 6.1 Centrifugation with time setting

#### **Prerequisites**

- The centrifuge is switched on.
- The rotor has been inserted and attached correctly.
- The rotor has been loaded correctly.
- The rotor lid has been mounted correctly.
- Buckets can swing out freely.
- The centrifuge lid is closed.



#### WARNING! Risk of injury from improperly attached rotors and rotor lids.

- ▶ Only centrifuge with the rotor and rotor lid firmly tightened.
- ▶ If unusual noises occur when the centrifuge starts, the rotor or the rotor lid may not be attached properly. Stop the centrifugation immediately.


### **6.1.1** Setting the centrifugation time



1. Select the *Time* area on the home screen. The *Set Time* input window will open.



- 2. Set the centrifugation time.
- Value range: 1 s 99 h 59 min 59 s
- *Timed*: Set the centrifugation time.
- · Continuous: Continuous run



- 3. To set the start time for the centrifugation time, press button 1.
  - Immediately: Time counting starts immediately.
  - Selected Speed Reached: Time counting starts when 95% of the specified speed has been reached.
- Confirm the entry using *Confirm*.
   The set value for the centrifugation time is saved.
   The input window closes.

### 6.1.2 Setting the temperature

The centrifuge cools or keeps the set temperature if the centrifuge remains switched on.



1. Select the *Temperature* area on the home screen. The *Set Temperature* input window will open.



- 2. Set the temperature. Value range: -11 °C 40 °C
- 3. Confirm the entry using *Confirm*. The set value for the temperature is saved. The input window closes.

### 6.1.3 Setting the rotational speed or *g-force*



1. Select the *Speed* area on the home screen. The *Set Speed* input window will open.



- 2. Select rpm for rotational speed or rcf for g-force. Values that have already been entered will be converted automatically when you switch between rotational speed and g-force. The radius can only be set if rcf mode has been selected. If you switch to rpm mode after entering the radius, the previously entered radius is not applied.
  - rpm: Setting the rotational speed
  - rcf: Setting the g-force
- Radius: Setting the radius
- 3. Set the rotational speed.



The value range depends on the rotor used.

If the value range falls below or exceeds the relevant thresholds, further navigation is only possible using the Back button under the number pad and the symbol for lower threshold violation or upper threshold violation.

4. Confirm the entry using *Confirm*. The set value for the rotational speed or *g-force* is saved. The input window closes.



#### Selected rcf mode in the Speed area

- The set radius is displayed at the bottom right.
- The set radius is only displayed if it deviates from the maximum radius.

### 6.1.4 Setting the acceleration ramp and braking ramp



1. Tap the *Ramps* button on the home screen. The *Set Ramps* input window will open.



- 2. Select the level for the acceleration ramp (*Acceleration*).
  - The selection is shown on a blue background.
- 3. Select the level for the braking ramp (*Brake*). The selection is shown on a blue background.
- 4. Confirm the entry using Confirm.

# 6.1.5 Starting centrifugation

### Prerequisites

• The centrifuge lid is closed.



1. Press *Start* to start the centrifugation run.



During centrifugation, the current values are shown in blue:

- · Remaining run time
- Current temperature in the rotor chamber
- Current rotational speed or *g-force*

The progress bar is shown as a gray bar at the start and filled in blue as time passes.

All set values are displayed in black.

The following values can be changed during the run:

- · Centrifugation time
- Temperature
- Speed
- Switch the display between *rpm* (rotational speed) and *rcf* (*g-force*).


### 6.1.6 End of centrifugation



1. Press *Stop* to end centrifugation before the set time.

The centrifuge stops automatically when the set time has elapsed.

The centrifuge lid remains sealed.



2. Press the *Open* button to open the closed centrifuge lid.

### 6.2 Starting centrifugation with the *Short Spin* function

#### **Prerequisites**

- The centrifuge is switched on.
- The rotor has been inserted and attached correctly.
- The buckets and adapters have been inserted correctly.
- The rotor has been loaded correctly.
- The rotor lid has been mounted correctly.
- · The buckets can swing out freely.
- The centrifuge lid is closed.



#### WARNING! Risk of injury from improperly attached rotors and rotor lids.

- ▶ Only centrifuge with the rotor and rotor lid firmly tightened.
- ▶ If unusual noises occur when the centrifuge starts, the rotor or the rotor lid may not be attached properly. Stop the centrifugation immediately.

### 6.2.1 Making Short Spin settings

The maximum speed is set by default for the *Short Spin* centrifugation.

1. To change the speed setting, change the selection under Settings>Device Settings>Short Spin.

### 6.2.2 Starting and stopping *Short Spin* centrifugation

- 1. To start the *Short Spin* centrifugation, press and hold the *short* button on the home screen.
  - The centrifugation run starts.
  - The current speed (rpm/rcf) appears.
- 2. To end the Short Spin centrifugation, release the short button.
  - The centrifugation run is ended.
  - · The rotor decelerates.
- 3. To open the lid, press the *open* button.



The set acceleration ramp/braking ramp does not work during Short Spin centrifugation.

### 6.3 Starting a temperature control run with the *FastTemp* function

Using the *FastTemp* function you can start a temperature control run directly without samples at a rotor and temperature-specific speed in order to quickly adjust the rotor chamber incl. the rotor and adapters to the set temperature.

#### **Prerequisites**

- · The centrifuge is switched on.
- The rotor has been inserted and attached correctly.
- The buckets and adapters have been inserted correctly.
- The rotor lid has been mounted correctly.
- The buckets can swing out freely.
- The centrifuge lid is closed.

### 6.3.1 Making FastTemp settings

1. Select the desired temperature in the *Temperature* area on the home screen.

### 6.3.2 Performing a temperature control run

- 1. Tap the FastTemp button.
  - The temperature control run starts.
  - The display shows the expected duration, the current speed and the message *Preparing Temperature...*.
  - The temperature control run ends automatically when the set temperature is reached.
  - · The speed decreases.
  - When the temperature control run is finished, the message *Ready* appears in the *Temperature* area and a signal tone sounds.
  - The time that has elapsed since the end of the temperature control run is shown on the display.
- 2. Confirm the message Fast Temp finished to be able to perform other functions.
  - No parameters can be changed during the temperature control run.

Centrifugation Centrifuge 5910 Ri English (EN)

54

### 7 User administration

# 7.1 The user management concept

User management can be used to organize access to the device. There are three user roles:

- Administrator
- User with standard rights
- User with restricted rights

#### 7.1.1 Administrator

The administrator has additional rights:

- Configuring the device
- Access to user management

### 7.1.2 User with standard rights

This user is allowed to use the device without restrictions, create new programs and favorites.

# 7.1.3 User with restricted rights

This user is allowed to use the device with restrictions, e.g., select, start and stop an existing program.

### 7.1.4 User rights without user management

Without user management, all users have the same rights as an administrator.

### 7.1.5 User rights

Tasks	User with restricted rights	User with standard rights	Administrator/ user (without user management)
Function related			
Access to Set Point Dialogs	_	×	×
Start centrifugation	×	×	х
Stop centrifugation	×	×	× Start
FastTemp Function	×	×	× Start
Short Spin Function	×	×	×
Open centrifuge	×	×	×


Tasks	User with restricted rights	User with standard rights	Administrator/ user (without user management)
Enable/exit standby	×	×	×
Acknowledge message			
Acknowledge message warning	×	×	×
Acknowledge message alarm	_	×	×
Acknowledge message error	_	×	×
Product-specific featur	es 1 (favorites)	-	
Access to favorites preview	×	×	×
Load and display favorites	_	×	×
Load favorites function in SP dialog	_	×	×
Product-specific featur	es 2 (programs)		
Access to program selection	×	×	×
Load program	×	×	×
Update parameters	_	×	×
Rename	_	×	×
Program protection (lock/unlock)	_	×	×
Delete	_	×	×
Display information	×	×	×
Product-specific featur	es 3 (Run Records)	•	
Access to Full Run Records	×	×	×
Filters	×	×	×
Export	×	×	×
Product-specific device	settings		
Short Spin	Read and edit	Read and edit	Read and edit
User settings			
User key in menu	_	×	×
User list with all features	Read	Read	Read
Add user	_	_	×

Tasks	User with restricted rights	User with standard rights	Administrator/ user (without user management)
Remove other users	_	_	×
Change your own user name	_	_	_
Change someone else's user name	_	_	_
Change your own name	×	×	×
Change someone else's name	_		×
Change your own e-mail address	×	×	×
Change someone else's e-mail address	_	_	×
Change your own user ID	_	_	×
Change someone else's user ID	_	_	×
Change your own user role	_	_	_
Change your own password/PIN	×	×	×
Reset someone else's password/PIN	_	_	×
General UI features		•	•
Full Event Log	×	×	×
Messages	Read	Read	Read
Clean display	×	×	×
Export	×	×	×
Export information for service	×	×	×
Export all other entries	×	×	×
Contact and support	Read and contact	Read and contact	Read and contact
General settings	•		•
Load setting into menu	×	×	×
about	Read	Read	Read
about/Name	Read	Read	Read and edit
about/Location	Read	Read	Read and edit
about/License informationen	Read	Read	Read

Tasks	User with restricted rights	User with standard rights	Administrator/ user (without user management)
Device settings/ Acoustic signals/Switch	Read	Read	Read and edit
Device settings/ Acoustic signals/Test key	× only when switch is active	× only when switch is active	× only when switch is active
Device settings/Display settings	Read and edit	Read and edit	Read and edit
Device settings/ Date-time	×	×	×
Device settings/ Network	Read	Read	Read and edit
Access to user management	_	_	×
User management/ Unrestricted user	n/a	n/a	×
User management/ Restricted user	n/a	n/a	×
User management/ Automatic logout	n/a	n/a	×
User management/ Login mode	n/a	n/a	×
User management/ Grant all users extra privileges	n/a	n/a	×
Service interface	_		_

# 7.2 Setting up user management

### 7.2.1 Creating an administrator




- 1. Tap the *Menu* button and navigate to the *Settings* > *User Management* menu item.
- 2. To enable user management, slide the *User Management* switch to the *I* position.

  The *Login mode* window appears.




- 3. Define the login mode for all users.
- 4. Continue the process with *Continue*. The *Administrator credentials* window appears.



- 5. Enter the user name for the first administrator in the *Enter User Name* field.
- 6. Continue the process with *Continue*. The *Administrator credentials* window appears.



- 7. Enter the PIN or password in the Enter PIN/ Password field. Confirm the entry via the Repeat PIN/Password field.
- Continue the process with Continue.
   The User Management succesfully enabled window appears.
   User management has been enabled.
   The user account for the first administrator has been created.



Confirm the message.
 The *User Management* window appears.
 It is now possible to edit user management.


# 7.2.2 Editing user management

#### **Prerequisites**

• The administrator is logged in.



1. Tap the *Menu* button and navigate to the *Settings* > *User Management* menu item.



2. Define the settings for user management.

- User Management: Switch user management on and off.
- Automatic Logout: Define the time after which a user is automatically logged out if the touchscreen is not used
- Login Mode: Define the login mode for all users.
- *Grant all users extra privileges*: Restricted rights (*Restricted User*) or standard rights (*User*) are active for all users.



When the *Grant all users extra privileges* option is enabled a login is not necessary. Even users not registered in user management can use the device with the rights that have been set (*Restricted User I User*).

### 7.2.3 Disabling user management



### NOTICE! Data loss when user management is disabled

Disabling user management deletes all user accounts.


- ▶ Check whether disabling user management is necessary.
- ▶ Inform all users that the user accounts have been deleted.

### Prerequisites


• The administrator is logged in.



- 1. Tap the *Menu* button and navigate to the *Settings* > *User Management* menu item.
- To disable user management, slide the *User Management* switch to the 0 position.
   The *Disabling User Management* window appears.



3. Continue the process with *Continue*. The *Confirm deleting all user accounts* window appears.



- 4. Enter the password/PIN.
- 5. Complete the process with *Continue*.

  User management is disabled. All user accounts are deleted.

### 7.3 Editing user accounts as an administrator



#### NOTICE! Risk of data loss due administrator password loss

The administrator is able to change his password or PIN only with his access data. If the administrator's access data is lost, changes cannot be made to the user administration and to the system settings.

In this case, the device will have to be reset to the factory settings by an authorized service technician. All user accounts and any data and settings stored on the device will be deleted.

- Create a second user account with administrator rights.
- ▶ Keep the administrator password secure.

### 7.3.1 Creating a user account



You can create 999 user accounts.

#### Prerequisites

• The administrator is logged in.



- 1. Tap the *Menu* button and navigate to the *User* menu item.
  - The list with the user accounts is displayed.
- 2. Tap the Add User button.

The Enter User Name for the new user field appears.



- 3. Enter the user name.
- 4. Confirm your entry.

The *User credentials* window appears.

The user account is created. The user data appears in the window.

The user is assigned to the user group *Restricted User*.



- 5. **Optional export of user data:** Connect the USB stick and tap the *Export* button.
- 6. Confirm the export.

The user data is exported to the USB stick in a TXT file.

- 7. If the export is successful, the *Export successful* window appears.
  - To complete the process, confirm the message.

### 7.3.2 Editing user accounts




Users with restricted user rights or standard rights can only edit their own *Full Name* and *E-mail* entries. Users can always change their own PIN or password.

Administrators can assign a new user ID to a user account and change the rights.

#### Prerequisites


• The administrator is logged in.





The list with the user accounts appears. Entries that can be edited are indicated by a black pen.

- 2. Select the user account.
- 3. Optional: Enter the full name.
- 4. Optional: Enter the e-mail address.
- 5. To change the user ID, tap *User-ID*.
- 6. Select the new user ID.



The list with the available user groups appears.

- 8. Assign a user group to the user.
  - Restricted User
  - User
  - Administrator

The selected parameters are stored and appear in the user account.



### 7.3.3 Deleting a user account

#### Prerequisites

· The administrator is logged in.



- 1. Tap the *Menu* button and navigate to the *User* menu item.
  - The list with the user accounts appears.
- 2. Select the user account to be deleted.
- 3. Tap the *Recycle bin* symbol.

  The *Confirm the deletion of:* window appears.



4. Confirm that you want to delete the user account. The user account is deleted.

### 7.3.4 Resetting the password/PIN for a user account

If a user has forgotten their password/PIN, the administrator can generate a new password.



The administrator can only change their password or PIN with their current access data. If the administrator's access data is lost, changes are no longer possible in the user administration. In this case, the device must be reset to the factory settings by an authorized service technician. All user accounts and the programs, log files and logs stored on the device will be deleted.

▶ Create a second user account with administrator rights.

#### Prerequisites

· The administrator is logged in.



- 1. Tap the *Menu* button and navigate to the *User* menu item.
  - The list with the user accounts appears.
- 2. Select the user account.
- 3. Tap the *Reset Password/PIN* button. The *Do you want to reset the Password/PIN for:* window appears.
- Confirm the process with Reset.
   The New Credentials window appears.
   The new password/PIN is created automatically.



- 5. To export the user data, connect the USB stick and tap the *Export* button.
- Confirm the export.The user data is exported to the USB stick in a TXT file.
- 7. If the export is successful, the *Export successful* window appears.
  - To complete the process, confirm the message.

# 7.4 Administrating your own user account

Users can only edit their own *Full Name* and *E-mail* entries. Users can always change their own PIN or password.

### Prerequisites

• The user is logged in.



- 1. Tap the *Menu* button and navigate to the *User* menu item.
  - The list with the user accounts appears. Entries indicated by a black pen can be edited.
- 2. Select the user account.
- 3. Optional: Enter the full name.
- 4. Optional: Enter the e-mail address.
- 5. To change the password/PIN, tap the *Change Password/PIN* button.
- 6. Enter the current password/PIN in the *Enter current Password/PIN* field.
- 7. Enter the new password/PIN in the Enter new Password/PIN and Repeat new Password/PIN fields.
- 8. Confirm your entry.

The message Password/PIN successfully changed appears.

The new password or the new PIN is active.

User administration Centrifuge 5910 Ri English (EN)

66

### 8 Programming

#### 8.1 Favorites function



If user management is enabled, the *Favorites* function is linked to user rights. Users with restricted rights cannot create or modify favorites.

### 8.1.1 Accessing the Favorites function

The device is delivered with favorites which can all be overwritten by individual favorites.



1. Tap the *Favorites* button on the home screen. The saved favorites for *Time*, *Temperature* and *Speed* are displayed.



If a favorite in the *Speed* category is displayed grayed out, the set rotational speed or g-force is not compatible with the rotor used.

### 8.1.2 Creating a favorite for *Time*, *Temperature* and *Speed*

*Time, Temperature* and *Speed* each specify a permitted value range that cannot be fallen below or exceeded when creating favorites.

In the *Speed* category the favorites can be composed of rpm entries and rcf entries.

- 1. Enter the parameters for Set Time, Set Temperature or Set Speed.
  - In Set Speed the radius cannot be saved in favorites.
- 2. Tap Add to Favorites.
- 3. Select a position for the favorite entry.
- 4. Confirm your selection.


The favorite in the selected position is overwritten.

### 8.2 *Programs* function



If user management is enabled, the *Programs* function is linked to user rights. Users with restricted rights can start programs, but not create or modify them.

### 8.2.1 Accessing the *Programs* function



► Tap the *Programs* button on the home screen. The list of all programs is displayed.



If programs contain parameters that are not compatible with the rotor used, a red icon with a crossed-out rotor appears behind the program name.

### 8.2.2 Creating a program

99 programs can be created. The order is freely selectable and program entries do not have to follow each other directly.

#### Prerequisites

- The parameters for *Time, Temperature, Speed* and *Ramps* have been set.
- 1. Tap on an empty program field.
- 2. Enter the program name.
- 3. Confirm the entry.


The set parameters are stored in the program.

The program appears in the list.

#### 8.2.3 Managing programs

A program can be managed via the options menu. The following options are available:

- Save Current Parameters: overwrite the parameters stored in the program with the currently set parameters
- Rename: change the name of the program
- Lock/Unlock: lock or unlock the program to protect it from being overwritten or enable it to be overwritten
- Delete: delete the program
- Show Info: show the parameters stored in the program
  - 1. Navigate to the corresponding program.
  - 2. Tap the options menu.




3. Select the required option.

Programming Centrifuge 5910 Ri English (EN)

70


# 9 Settings

# 9.1 Accessing settings



- 1. Tap the *Menu* button.
- Tap the Settings button.The following menu items are displayed:
  - · About this Centrifuge 5910 Ri
  - System Settings
  - Device Settings
  - User Management
- Maintenance and Qualification


### 9.2 About this Centrifuge 5910 Ri



- ▶ Tap the *About this Centrifuge 5910 Ri* button. The following information can be accessed:
- *Name*: The device name can be entered by the administrator.
- *Registration Number*: The registration number can be entered by the administrator.
- Location: Location information can be entered by the administrator.
- · Article number
- · Serial number
- Software Version
- License Information


### 9.3 System Settings

### 9.3.1 Accessing System Settings



- ► Tap the *System Settings* button. The following settings can be made.
- Date & Time: Set the date, time and time zone.
- Network: Set the parameters for network operation.
- VisioNize Setup: Connect the device to the cloud.

### 9.3.2 Accessing *Date & Time* settings





If the date, time or time zone are changed, Run Record/Event Log may be sorted incorrectly.



The current local time and the current date must be set on devices which are controlled by the VisioNize software.

#### Setting the date and time automatically

### Prerequisites

- The device is connected to the network. A time server is available.
- 1. Tap the Date & Time button.
- 2. Use the *Automatic date & time* switch to enable the function.
- 3. Tap the Select timezone button.
- 4. Select the continent and the time zone.

#### Setting the date and time manually


- 1. Tap the Date & Time button.
- 2. Use the *Automatic date & time* switch to disable the function.
  - Set date and Set time can be selected.
- 3. Tap the Set date button and enter the date.
- 4. Tap the Set time button and enter the time.
- 5. Tap the Select timezone button.
- 6. Select the continent and the time zone.

### 9.3.3 Accessing Network settings



The device can be connected directly to the Internet and to an internal network. There is no Internet connection required for operation. If the device is connected to the Internet, the owner is responsible for data security.

- ▶ A connection to the internal network or the Internet may only be made by a network administrator.
- ▶ Check the settings for the internal network or the Internet before making a connection.



- Tap the *Network* button.
   The following settings can be made.
- IP Adresses: Current IP address of the device.
- *MAC Adresses*: Number by which the device can be uniquely identified in the network.
- Enable OPC/REST access: The device allows communication with an external software via OPC or REST.
- Enable DHCP: The device uses an IP address which has been assigned to it by an existing DHCP server.
- Manual Setup: Enables a window. This window can be used to enter the network settings manually if no DHCP server is available. Manual Setup can only be selected if automatic IP address assignment (Enable DHCP) is switched off.
- Self signed certificate: This function is intended only for authorized service personnel.
- Extended network log: This function is intended only for authorized service personnel.

## 9.3.4 Activating Manual Setup

- 1. Use the switch to disable the *Enable DHCP* function. *Manual Setup* can be selected.
- 2. Tap the Manual Setup button.
- 3. Complete the entries in the input window and confirm.


## 9.3.5 Accessing VisioNize Setup

To connect the device to the cloud at a time later than registration, perform the following steps:

- 1. Start the registration for VisioNize via Settings > System Settings > VisioNize Setup.
- 2. Follow the instructions for registration(see *Registering for VisioNize on p. 27*).


# 9.4 Device Settings

# 9.4.1 Accessing Device Settings



- ► Tap the *Device Settings* button. The following settings can be made.
- Display Settings: Set brightness and power saving mode.
- *Language*: Select the language for the user interface.
- Short Spin: Set a specific rotor rotational speed or select the maximum rotor rotational speed.
- *Sound Settings*: Enable/disable the acoustic alarm and the end-of-program sound.

## 9.4.2 Display Settings



- Tap the Display Settings button.
   A selection list for setting the Display brightness, Engergy save mode and Display timeout appears.
- Tap the *Display brightness* button.
   The slider control bar for the brightness setting is displayed.
- 3. Set the brightness.
- 4. Use the *Engergy save mode* switch to enable or disable the power saving mode.

  When the *Engergy save mode* is enabled, the *Display timeout* button becomes active.
- Tap Display timeout.A window for entering the time appears.
- 6. Enter the time.


  The brightness of the display is dimmed if there is no input during the selected interval.

## 9.4.3 Language




- Tap the Language button.
   The language selection for the user interface is displayed.
- 2. Select the required language.
- Switch the centrifuge off and back on. New text modules for the selected language are loaded.

# 9.4.4 Short Spin



- Tap the Short Spin button.
   The selection for the rotor rotational speed is displayed.
- Select the entered rotor rotational speed or the maximum rotor rotational speed.
   The Short Spin function is performed with the selected rotor rotational speed.


# 9.4.5 Sound Settings



- 1. Tap the Sound Settings button.
- 2. Enable or disable the acoustic alarm.
- 3. Enable or disable the signal tone for the end of the program.

# 9.5 Adding service intervals

# 9.5.1 Accessing Maintenance & Qualification



- ► Tap the *Maintenance & Qualification* button. The following selection appears:
- Recurring Tasks: Add service interval.
- Rotor Health: Display information on the number of cycles of the rotors.

# 9.5.2 Adding Recurring Tasks



- 1. Tap the Recurring Tasks button.
- 2. Tap the Add button.
- 3. Enter a name for the new service task and confirm with *next*.
- 4. Enable the *Task Policy* function and confirm with *continue*.
- Enter the time interval for the service task and confirm with the *Finish* button.
   The new service interval is displayed in the selection list on the left-hand side.
- 6. Tap the *Edit* button.

  The *Task Policy* selection window for the activation of the service reminder is displayed.
- 7. Enable or disable the service reminder and confirm the selection with *continue*.
- 8. Set the time interval for the service task and confirm with *finish*.

The service interval with the time and reminder information appears in the list.

#### 9.5.3 Rotor Health

The centrifuge automatically detects the inserted rotor. The maximum number of cycles of the rotors is set by the manufacturer and cannot be changed. The number of cycles completed can be queried in the *Maintenance & Qualification* menu.

# 10 Maintenance

## 10.1 Service



## WARNING! Risk of injury due to defective gas spring(s).

A defective gas spring is an insufficient support for the centrifuge lid. There is a risk of crushing fingers or limbs.

- ▶ Ensure that the centrifuge lid can be opened completely and that it remains in this position.
- ▶ Regularly check all gas springs for their proper function.
- ▶ Have defective gas springs replaced immediately.
- ▶ Have gas springs replaced by a service technician every 2 years.




#### WARNING! Risk of fire or electrical shock

▶ Have the centrifuge's electrical safety, especially the paths for the protective connections, checked every 12 months by trained and skilled personnel.

In the Maintenance & Qualification>Recurring Tasks menu, the service intervals stored under Settings>Maintenance & Qualificaton>Recurring Tasks can be called and confirmed.

## 10.1.1 Confirming Recurring Tasks

1. In the Settings menu, tap on Maintenance Qualification.



2. Select the Recurring Tasks area.



Information on the selected service work is displayed.

3. Tap the Perform Task button to confirm the service work performed and reset the service interval.

We recommend to have the centrifuge and the associated rotors checked by Technical Service during a service at least every 12 months. Please note the country-specific regulations.

# 10.1.2 Displaying Rotor Health

1. In the Settings menu, tap on Maintenance Qualification.



2. Select the Rotor Health area.



A list of the rotors used so far appears with the number of cycles completed.

# 10.2 Preparing cleaning/disinfection

- ▶ Clean all accessible surfaces of the device and the accessories at least weekly and when contaminated.
- ▶ Clean the rotor regularly. This way the rotor is protected and the durability is prolonged.
- ▶ Furthermore, observe the notes on decontamination (see *Decontamination before shipment on p. 84*) when the device is sent to the authorized Technical Service for repairs.

The procedure described in the following chapter applies to the cleaning as well as to the disinfection or decontamination. The table below describes the steps required on top of this:

Cleaning	Disinfecting/decontamination				
<ol> <li>Use a mild cleaning fluid to clean the accessible surfaces of the device and the accessories.</li> <li>Carry out the cleaning as described in the following chapter.</li> </ol>	<ol> <li>Choose the disinfection method which corresponds to the legal regulations and guidelines in place for your range of application. For example, use alcohol (ethanol, isopropanol) or alcohol-based disinfectants.</li> <li>Carry out the disinfection or decontamination as described in the following chapter.</li> <li>Then clean the device and the accessories.</li> </ol>				



If you have any further questions regarding the cleaning and disinfection or decontamination or regarding the cleaning fluid to be used, contact the Eppendorf AG Application Support. The contact details are provided on the back of this manual.

# 10.3 Performing cleaning/disinfection



#### DANGER! Electric shock due to the ingress of liquid.

- ▶ Switch off the device and disconnect it from the mains/power line before commencing any cleaning or disinfection procedures.
- ▶ Do not allow any liquids to penetrate the inside of the housing.
- ▶ Do not spray clean or spray disinfect the housing.
- ▶ Only reconnect the device to the mains/power line when it is completely dry, both inside and outside.



NOTICE! Danger due to deformed or brittle tubes. Autoclaving at excessive temperatures can lead to plastic tubes becoming brittle and deformed.

This could cause damage to the device and the accessories and sample loss.

- ▶ Observe the temperatures specified by the manufacturer when autoclaving tubes.
- ▶ Do not use deformed or brittle tubes.



#### NOTICE! Damage from the use of aggressive chemicals.

- ▶ Do not use any aggressive chemicals on the device or its accessories, such as strong and weak bases, strong acids, acetone, formaldehyde, halogenated hydrocarbons or phenol.
- ▶ If the device has been contaminated by aggressive chemicals, clean it immediately using a mild cleaning agent.



#### NOTICE! Corrosion due to aggressive cleaning agents and disinfectants.

- ▶ Do not use any corrosive cleaning agents, aggressive solvents or abrasive polishes.
- ▶ Do not incubate the accessories in aggressive cleaning agents or disinfectants for longer periods.



#### NOTICE! Damage from UV and other high-energy radiation.

- ▶ Do not use UV, beta or gamma, or any other high-energy radiation for disinfection.
- ▶ Avoid storage in areas with strong UV radiation.



#### **Autoclaving**

Fixed-angle rotors, rotor lids, adapters, and buckets can be autoclaved (121 °C, 20 min). Rotor crosses of swing-bucket rotors cannot be autoclaved.

Replace the seal on aerosol-tight rotor lids and aerosol-tight caps after 50 autoclaving cycles.



#### Aerosol tightness

Check that the seals are intact before use.

Replace the rotor lids with screw cap when the sealing rings on the lid screw and in the lid groove become worn.

Regular care of the sealing rings is necessary in order to protect the rotors.

Aerosol-tight rotors should never be stored with the lids screwed on!

In order to prevent damage, lightly grease the lid threads of aerosol-tight rotors regularly with pivot grease (order no. int.: 5810 350.050/North America: 022634330).

## 10.3.1 Cleaning and disinfecting the device


#### Recommended cleaning agents:

- Alcohol 70 % (ethanol, isopropanol)
- · Mild neutral cleaning agent
- 1. Open the lid. Switch the device off at the mains/power switch. Disconnect the mains/power plug from the voltage supply.
- 2. Remove the rotor.
- 3. Clean and disinfect all accessible surfaces of the device, including the mains/power cord, using a damp cloth and the recommended cleaning agents.
- 4. Thoroughly clean the rubber seal of the rotor chamber with water.
- 5. Rub the dry rubber seal with glycerol to prevent it from becoming brittle. Other components of the device, such as the motor shaft and rotor cone, must not be lubricated.
- 6. Clean the motor shaft with a soft, dry, lint-free cloth. Do not grease the motor shaft.
- 7. Inspect the motor shaft for damage.
- 8. Inspect the device for corrosion and damage.
- 9. Leave the centrifuge lid open when the device is not being used.
- 10. Only reconnect the device to the mains/power supply if it is fully dry on the inside and outside.


## 10.3.2 Cleaning and disinfecting the rotor

- 1. Inspect the rotor and accessories for damage and corrosion. Do not use any damaged rotors or accessories.
- 2. Clean and disinfect the rotors and accessories with the recommended cleaning agents.
- 3. Clean and disinfect the rotor bores with a bottle brush.
- 4. Clean and disinfect the rotor lid.

QuickLock rotor lids: Remove the sealing ring. Clean the sealing ring and the groove below it.



5. Rinse the rotors and accessories thoroughly with distilled water. Rinse the rotor bores of fixed-angle rotors particularly thoroughly.




6. Place the rotors and accessories on a towel to dry. Place the fixed-angle rotors with the rotor bores facing down so the bores can dry.

- 7. Coat the sealing ring of the rotor lid with a thin layer of pivot grease and correctly reinsert it in the clean and dry groove.
- 8. Clean the rotor cone with a soft, dry, lint-free cloth. Do not lubricate the rotor cone.
- 9. Inspect the rotor cone for damage.
- 10. Place the dry rotor onto the motor shaft.
- 11. Tighten the rotor nut firmly by turning it **clockwise** with the rotor key.
- 12. Leave the rotor lid open when the rotor is not being used.

#### 10.3.3 Changing the seal of the aerosol-tight cap

To clean the aerosol-tight cap, remove the seal of the aerosol-tight cap.

#### 10.3.3.1 Removing the seal



- Use a blunt lever to lift the seal out of the groove (e.g., use the round side of a paper clip).
   Make sure not to damage the seal with the wire ends.
- 2. Carefully lift the seal out of the groove.

# 10.3.3.2 Inserting the seal



## NOTICE! Faulty sealing if the seal is handled incorrectly.

- ▶ Insert the seal evenly.
- ▶ Do not pull the seal lengthwise.
- Check that the seal is not damaged.
   Do not use any damaged, discolored or dirty seals.
- 2. Place the seal on the groove and slightly press it into the groove.
- 3. Place the cap on the bucket and close it completely.
- 4. Remove the cap and check the correct positioning of the seal.



If the seal is too long or too short, remove the seal from the groove. Insert the seal again.

# 10.4 Additional care instructions for refrigerated centrifuges.

- ▶ Regularly clear the rotor chamber of ice formations via defrosting, either by leaving the centrifuge lid open or carrying out a brief temperature control run at approx. 30°C.
- ▶ To relieve the gas springs in the centrifuge lid, leave the centrifuge lid open when not in use for a long period.

Residual moisture can escape.

- ▶ Wipe up condensation water in the rotor chamber. Use a soft absorbent cloth for this.
- No later than every 6 months, remove any dust deposits from the ventilation gaps of the centrifuge using a brush or swab. First switch off the centrifuge and remove the mains/power plug.

# 10.5 Cleaning glass breakage

When using glass tubes there is a risk of glass breakage in the rotor chamber. The resulting glass splinters are swirled around in the rotor chamber during centrifugation and have a sandblasting effect on the rotor and accessories. The smallest glass particles become lodged in the rubber parts (e.g., the motor guide, the rotor chamber seal, and the rubber mats of adapters).



#### **NOTICE!** Glass breakage in the rotor chamber

Glass tubes in the rotor chamber may break if the g-force is too high. Broken glass can damage the rotor, accessories and samples.

▶ Please note the manufacturer's information on the recommended centrifugation parameters (load and speed).

#### Effects of glass breakage in the rotor chamber:

- Fine black metal abrasion in the rotor chamber (in metal rotor chambers)
- The surfaces of the rotor chamber and accessories are scratched.
- The chemical resistance of the rotor chamber is reduced.
- Contamination of samples
- Wear on rubber parts

#### How to proceed in case of glass breakage

- 1. Remove all splinters and glass powder from the rotor chamber and accessories.
- 2. Thoroughly clean the rotor and rotor chamber. Thoroughly clean the bores of the fixed-angle rotors, in particular.
- 3. If required, replace the rubber mats and adapters to prevent any further damage.
- 4. Regularly check the rotor bores for deposits and damage.

# 10.6 Resetting the excess current switch

Thermal excess current switches are mounted as fuses. If the excess current protection is triggered, they set the switch to OFF. However, they do not automatically switch it on again.

To switch on the excess current switch again, proceed as follows:

- 1. Switch off the centrifuge using the mains/power switch.
- 2. Wait for at least 20 s and switch on the centrifuge again.

The excess current switch is reactivated and the centrifuge is ready for operation.

# 10.7 Decontamination before shipment

If you are shipping the device to the authorized Technical Service for repairs or to your authorized dealer for disposal please note the following:



#### WARNING! Risk to health from contaminated device.

- 1. Observe the information in the decontamination certificate. It is available as a PDF document on our webpage (<a href="https://www.eppendorf.com/decontamination">www.eppendorf.com/decontamination</a>).
- 2. Decontaminate all the parts to be shipped.
- 3. Include the fully completed decontamination certificate in the shipment.

# 10.8 Performing a software update

#### Checking the software version on the device

1. Check which software version is installed on the device. Tap the menu path *Menu > Settings > About this Centrifuge 5910Ri*.

The software version is displayed below Software Version.

#### Requesting a software update

- 2. Request data for the software update from your local Eppendorf partner. The address can be found on the Internet at <a href="https://www.eppendorf.com">www.eppendorf.com</a>.
- 3. Save the **update.zip** file with the software update on a USB stick.
- 4. Unzip the update.zip file.



The device has only access to data on the top level of the USB stick.

• Do not save the data in a folder.

#### Performing a software update

- 5. Connect the USB stick with the software update to the device.
- 6. Switch on the device.

The Centrifuge 5910 Ri is started from the USB stick.

7. Follow the instructions on the device until the software update is complete.



Do not abort the software update. If the update is stopped, this will result in loss of data and the device will have to be reset to the factory settings. Contact the authorized service in this case.

Maintenance Centrifuge 5910 Ri English (EN)

86

# 11 Troubleshooting

# 11.1 General errors

Technical faults may be triggered by faults such as a mains/power failure or mains/power fluctuations.

In most cases one of the following measures is sufficient:

# 11.1.1 Restarting the software

▶ Switch off the device and switch it back on after approx. 10 seconds.

# 11.1.2 Checking the cable connections

- 1. Switch off the device.
- 2. Check the cable connections.
- 3. Switch on the device.

# 11.1.3 Entering contacts

Information on your Eppendorf partners can be entered in this area.

## 11.1.3.1 Contacts & Support

- 1. Tap the *Menu* button.
- 2. Tap the Contacts & Support button.

A selection list appears.

- Contact: Saving service contacts is possible.
- *Diagnostics*: Product-specific information can be called up by the customer under the guidance of the service department.

Alternatively, you can find your local Eppendorf partner on the Internet at www.eppendorf.com.

# 11.2 Emergency release

If the centrifuge lid cannot be opened, you can activate the emergency release manually.



#### WARNING! Risk of injury from rotating rotor.

If the emergency release of the lid is activated, the rotor may continue to rotate for several minutes.

- ▶ Wait for the rotor to stop before activating the emergency release.
- ▶ To check, look through the monitoring glass in the centrifuge lid.

Use the rotor key delivered with the Centrifuge 5910 Ri for the emergency release. Carry out the following steps on both the left side and right side of the centrifuge.

- 1. Pull out the mains/power plug and wait for the rotor to stop.
- 2. Insert the rotor key into the hexagonal opening on one side of the centrifuge until noticeable resistance can be felt.
- 3. Slightly press and turn the rotor key **counterclockwise**.
- 4. Insert the rotor key into the hexagonal opening on the opposite side of the centrifuge until noticeable resistance can be felt.
- 5. Slightly press and turn the rotor key **counterclockwise**. This will release the centrifuge lid.
- 6. Open the centrifuge lid.

# 12 Transport, storage and disposal

# 12.1 Transport



## CAUTION! Risk of injury due to lifting and carrying heavy loads

The device is heavy. Lifting and carrying the device can lead to back injuries.

- Only transport and lift the device with an adequate number of helpers.
- ▶ Use a transport aid to transport the device.
- Remove the rotor from the centrifuge before transport.
- Use the original packaging and the transport securing devices for transport.

	Air temperature	Relative humidity	Atmospheric pressure		
General transport	-25 °C – 60 °C	10 % – 75 %	30 kPa – 106 kPa		
Air freight	-20 °C – 55 °C	10 % – 75 %	30 kPa – 106 kPa		

# 12.2 Storage

	Air temperature		Atmospheric pressure		
In transport packing	-25 °C – 55 °C	10 % – 75 %	70 kPa – 106 kPa		
Without transport packing	-5 °C – 45 °C	10 % – 75 %	70 kPa – 106 kPa		

# 12.3 Disposal

The product must be disposed of in accordance with the relevant legal provisions.

# Information on the disposal of electrical and electronic devices in the European Community:

Within the European Community, the disposal of electrical devices is regulated by national regulations based on EU Directive 2012/19/EU pertaining to waste electrical and electronic equipment (WEEE).

According to these regulations, any devices supplied after August 13, 2005, in the business-to-business sphere, to which this product is assigned, may no longer be disposed of in municipal or domestic waste. They are marked with the following symbol to indicate this:



As the disposal regulations may differ from one country to another within the EU, please contact your supplier for more information.

# 13 Technical data13.1 Power supply

Mains/power connection	230 V, 50 Hz – 60 Hz 120 V, 50 Hz – 60 Hz 100 V, 50 Hz – 60 Hz
Current consumption	230 V: 10.5 A 120 V: 12 A 100 V: 15 A
Power consumption	230 V: Maximum 1650 W 120 V: Maximum 1440 W 100 V: Maximum 1500 W
EMC: Noise emission (radio interference)	230 V: EN 61326-1/EN 55011 – Class A 120 V: CFR 47 FCC Part 15 – Class A 100 V: EN 61326-1/EN 55011 – Class A
EMC: Noise immunity	EN 61326-1 industrial electromagnetic environment
Overvoltage category	II
Degree of pollution	2

# 13.2 Weight/dimensions

	Width: 71.5 cm Depth: 62.0 cm/68.0 cm Height: 36.8 cm/85.0 cm
Weight without rotor	109 kg

Rotor weights:		Accessories without caps	5:		
S-4×Universal 6790 g		Universal bucket	920 g		
S-4×750	5100 g	Round bucket	605 g		
		DWP bucket	700 g		
S-4×500 5400 g	5400 g	Bucket	585 g		
		Flex bucket	810 g		
		Form bucket 7x50	880 g		
S-4×400	5200 g	Round bucket	490 g		
FA-6×250	5450 g				
FA-6×50	3450 g				
FA-48×2	2500 g				
FA-20×5	2800 g				
FA-30×2	1800 g				
F-48×15	2100 g	Sleeve	30 g		

# 13.3 Noise level

The noise level was measured frontally in a sound measuring chamber with accuracy class 1 (DIN EN ISO 3745) at a distance of 1 m from the device and at lab bench height.

	Swing-bucket rotor	Fixed-angle rotor
Noise level at maximum rotor speed	< 53 dB(A) (S-4×Universal) < 57 dB(A) (S-4×750)	< 59 dB(A) (FA-6×50)

# 13.4 Ambient conditions

Environment	For indoor use only
Ambient temperature	10 °C – 35 °C
Relative humidity	10 % – 75 %, non-condensing
Atmospheric pressure	79.5 kPa – 106 kPa Use up to a height of 2 000 m above sea level.

# 13.5 Application parameters

Run time	10 s − 99:59 h, infinite (∞), • can be set in increments of 1 s
Temperature	-11 °C – 40 °C
Relative centrifugal force	$1 \times g - 22132 \times g$ • can be set in increments of $1 \times g$
Rotational speed	10 rpm – 14000 rpm • can be set in increments of 1 rpm
Maximum load	Fixed-angle rotor: 6 × 250 mL Swing-bucket rotors: 4 × 1000 mL
Maximum kinetic energy	36400 J
Permitted density of the material for centrifuging (at maximum <i>g</i> -force (rcf) or rotational speed (rpm) and maximum load)	1.2 g/mL 1.0 g/mL for rotor <b>FA-6×250</b>
Inspection obligation in Germany	Yes

# 13.6 Temperatures

Rotor	Temperature
S-4×Universal-Large	
230 V	4 °C ±2 °C
120 V	6 °C ±2 °C

# 13.7 Acceleration and deceleration times

The following table shows the approximate acceleration and deceleration times according to DIN 58970 for the rotors of the Centrifuge 5910 Ri. The data was determined with the rotor at maximum load. Fluctuations may occur depending on the condition of the device and the load.

- Level 9: shortest acceleration time/deceleration time
- Level 0: longest acceleration time/deceleration time (with the brake off)

Rotor		0	1	2	3	4	5	6	7	8	9
<b>S-4×Universal</b> (230 V, 120 V)	Acceleration time	506 s	294 s	208 s	144 s	108 s	86 s	80 s	73 s	68 s	64 s
	Deceleration time	1609 s	706 s	264 s	182 s	122 s	92 s	75 s	63 s	57 s	49 s
	Tolerance	_	-				±5 %	*			
S-4×Universal (100 V)	Acceleration time	911 s	484 s	329 s	225 s	159 s	124 s	107 s	92 s	83 s	73 s
	Deceleration time	1351 s	495 s	275 s	182 s	123 s	89 s	77 s	66 s	61 s	58 s
	Tolerance	_	_				±5 %	*			
<b>S-4×750</b> (230 V, 120 V)	Acceleration time	406 s	257 s	184 s	123 s	91 s	71 s	57 s	49 s	43 s	36 s
	Deceleration time	1017 s	383 s	235 s	157 s	106 s	82 s	69 s	54 s	44 s	35 s
	Tolerance	_	-				±5 %	*			
<b>S-4×750</b> (100 V)	Acceleration time	951 s	491 s	365 s	238 s	163 s	118 s	102 s	85 s	74 s	61 s
	Deceleration time	1223 s	494 s	220 s	149 s	102 s	78 s	63 s	52 s	46 s	39 s
	Tolerance	_	-				±5%	*			
<b>S-4×500</b> (230 V, 120 V)	Acceleration time	345 s	218 s	157 s	104 s	77 s	60 s	48 s	41 s	35 s	28 s
	Deceleration time	771 s	360 s	200 s	131 s	95 s	71 s	53 s	44 s	39 s	30 s
	Tolerance	_	_				±5 %	*			
<b>S-4×500</b> (100 V)	Acceleration time	880 s	455 s	339 s	221 s	152 s	110 s	92 s	79 s	67 s	52 s
	Deceleration time	932 s	375 s	204 s	138 s	96 s	71 s	57 s	49 s	40 s	34 s
	Tolerance	-	-				±5 %	*	-		

Rotor		0	1	2	3	4	5	6	7	8	9
<b>S-4×400</b> (230 V, 120 V)	Acceleration time	406 s	260 s	180 s	120 s	86 s	63 s	54 s	43 s	38 s	30 s
	Deceleration time	860 s	386 s	220 s	156 s	108 s	77 s	65 s	52 s	45 s	35 s
	Tolerance	_	-				±5 %	*			
<b>S-4×400</b> (100 V)	Acceleration time	1132 s	583 s	433 s	282 s	193 s	139 s	115 s	97 s	81 s	62 s
	Deceleration time	861 s	370 s	228 s	159 s	112 s	80 s	67 s	57 s	48 s	38 s
	Tolerance	_	-				±5 %	*			l .
<b>FA-6×50</b> (230 V, 120 V)	Acceleration time	351 s	239 s	167 s	115 s	85 s	63 s	55 s	46 s	40 s	34 s
	Deceleration time	686 s	330 s	215 s	154 s	107 s	77 s	62 s	49 s	41 s	31 s
	Tolerance	_	-				±5 %	*			
<b>FA-6×50</b> (100 V)	Acceleration time	619 s	414 s	280 s	190 s	136 s	102 s	87 s	71 s	62 s	53 s
	Deceleration time	750 s	338 s	215 s	154 s	109 s	79 s	65 s	52 s	43 s	32 s
	Tolerance	-	-	±5%*							
<b>FA-20×5</b> (230 V, 120 V)	Acceleration time	304 s	205 s	140 s	95 s	70 s	51 s	44 s	36 s	32 s	26 s
	Deceleration time	605 s	290 s	190 s	133 s	93 s	69 s	56 s	44 s	39 s	28 s
	Tolerance	-	-				±5 %	*			
<b>FA-20×5</b> (100 V)	Acceleration time	486 s	324 s	227 s	153 s	109 s	82 s	69 s	57 s	49 s	39 s
	Deceleration time	723 s	296 s	194 s	136 s	95 s	69 s	57 s	45 s	38 s	28 s
	Tolerance	-	_				±5 %	*			
<b>FA-48×2</b> (230 V, 120 V)	Acceleration time	251 s	169 s	117 s	80 s	58 s	44 s	37 s	30 s	28 s	22 s
	Deceleration time	546 s	235 s	151 s	107 s	77 s	55 s	46 s	37 s	32 s	24 s
	Tolerance	-	-				±5 %	*			l .
<b>FA-48×2</b> (100 V)	Acceleration time	382 s	249 s	175 s	118 s	88 s	64 s	55 s	46 s	34 s	32 s
	Deceleration time	565 s	226 s	153 s	111 s	80 s	57 s	47 s	38 s	33 s	24 s
	Tolerance	-	_				±5 %	*			

Rotor		0	1	2	3	4	5	6	7	8	9
<b>FA-30×2</b> (230 V, 120 V)	Acceleration time	245 s	164 s	114 s	77 s	57 s	44 s	37 s	31 s	26 s	21 s
	Deceleration time	359 s	224 s	147 s	103 s	74 s	51 s	43 s	35 s	29 s	23 s
	Tolerance	_	-				±5%	*			
<b>FA-30×2</b> (100 V)	Acceleration time	373 s	242 s	170 s	115 s	85 s	63 s	54 s	45 s	33 s	30 s
	Deceleration time	463 s	223 s	148 s	106 s	75 s	54 s	44 s	35 s	30 s	22 s
	Tolerance	_	-				±5%	*			
F-48×15 (230 V, 120 V)	Acceleration time	205 s	137 s	95 s	63 s	45 s	34 s	29 s	24 s	21 s	18 s
	Deceleration time	397 s	196 s	117 s	82 s	56 s	40 s	34 s	28 s	23 s	18 s
	Tolerance	_	-				±5 %	*			-
<b>F-48×15</b> (100 V)	Acceleration time	284 s	190 s	128 s	87 s	62 s	48 s	41 s	33 s	30 s	25 s
	Deceleration time	362 s	185 s	120 s	84 s	59 s	43 s	36 s	29 s	24 s	19 s
	Tolerance	_	-				±5 %	*			•

<sup>\* 5</sup> s minimum

## 13.8 Service life of accessories



#### **CAUTION!** Danger due to material fatigue.

If the service life is exceeded, it cannot be guaranteed that the material of the rotors and the accessories will withstand the stresses during centrifugation.

▶ Do not use accessories that have exceeded their maximum service life.

Eppendorf states the maximum service life of rotors and accessories in cycles and years. The number of cycles is decisive. If determination of the number of cycles is not possible, the service life in years applies.

Each centrifugation run during which the rotor is accelerated and braked is counted as a cycle, independent of the speed and the duration of the centrifugation run.

For the following rotors, the service life is based on the following standard laboratory day: Use for 25 cycles per day on 5 days a week, 52 weeks a year.

Fixed-angle rotor	Centrifuge	Max. service from the first commissioning onward		
		in cycles	in years	
F-48×15	5910 R, 5910 Ri	100000	15	
FA-6×50	5910 R, 5910 Ri, 5920 R	100000	15	
FA-20×5	5910 R, 5910 Ri, 5920 R	100000	15	
FA-30×2	5910 R, 5910 Ri	100000	15	
FA-48×2	5910 R, 5910 Ri, 5920 R	100000	15	
FA-6×250	5910 R, 5910 Ri	50000	7	
S-4×400	5910 R, 5910 Ri	100000	15	
S-4×500	5910 R, 5910 Ri	100000	15	
S-4×750	5910 R, 5910 Ri, 5920 R	100000	15	
S-4×Universal	5910 R, 5910 Ri	50000	7	

Unless stated otherwise (in the manual of the centrifuge, indication of the number of cycles on the rotor, in the instructions for use of the rotor), all other rotors and rotor lids can be used over the entire service life of the centrifuge if the following prerequisites are met:

- proper use
- recommended maintenance
- · undamaged condition

Accessories	Max. service from the first commissioning onward
Aerosol-tight rotor lids with an exchangeable seal (e.g., QuickLock rotor lids)	3 years (replace seals every 50 autoclaving cycles)
Aerosol-tight rotor lids without exchangeable seal	3 years or 50 autoclaving cycles, whichever occurs first
Non-aerosol-tight rotor lids	3 years
Aerosol-tight caps made of PP, PC, PEI	3 years or 50 autoclaving cycles, whichever occurs first
Adapters	1 year

The date of manufacture is stamped on the rotors in the format 03/15 or 03/2015 (= March 2015). On the inside of the plastic rotor lid, the date of manufacture is stamped in the form of a clock.

# To ensure aerosol tightness, the following applies:

- ▶ Replace aerosol-tight rotor lids without exchangeable seal and cap after 50 autoclaving cycles.
- ▶ Replace the seal of aerosol-tight rotor lids with exchangeable seal (e.g. QuickLock rotor lids) after 50 autoclaving cycles.

#### Rotors for the Centrifuge 5910 Ri 14



Eppendorf centrifuges may only be operated with rotors that are intended for use with the corresponding centrifuge.

▶ Only use rotors that are intended for use with the corresponding centrifuge.

Use only rotors labeled 5910R/Ri, 5910R or 59XX.

Please note the manufacturer's information on the centrifugation stability of the sample tubes used (maximum *g-force*).

#### 14.1 Rotor S-4×Universal

# 14.1.1 Swing-bucket rotor S-4×Universal with 4 universal buckets

50			Max. g-force:	$4347 \times g$
			Max. speed:	4500 rpm
Rotor	Universal bucket an	d aerosol-tight cap	Max. load per	
S-4×Universal			bucket (adapter,	
			tube and contents):	1595 g
	T	1	T	
Tube	Tube	Adapter	Bottom shape	Max. g-force
	Capacity		Diameter	Max. speed
	Number per adapter/rotor	Order no. (international)	Max. tube length with/without cap	Radius
	Conical tube	8800	Conical	4324 × g
	50 mL		Ø 29 mm	4500 rpm
	7/28	5910 751.001	121 mm/124 mm	19.1 cm
	Wide-neck bottle	\$50\c	Flat	4234 × g
	250 mL		Ø 62 mm	4500 rpm
	1/4	5910 751.001	139 mm/146 mm	18.7 cm
	Microplate		Flat	2604 × g
	96/384 wells			4500 rpm
	1/4	5910 751.001	–/16 mm	11.5 cm
<b>(h</b> )	Eppendorf Tubes	Rosa	Conical	4324 × g
Harden Street	5 mL		Ø 17 mm	4500 rpm
		5910 752.008		
		(without upper		
	16/64	part)	122 mm/124 mm	19.1 cm

Tube	Tube	Adapter	Bottom shape	Max. g-force	
	Capacity		Diameter	Max. speed	
	Number per adapter/rotor	Order no. (international)	Max. tube length with/without cap	Radius	
100	Conical tube	Poss	Conical	4324 × g	
17 (1940)	15 mL		Ø 17 mm	4500 rpm	
	17/64	5910 752.008	122 mm/124 mm	19.1 cm	
	Microplate	Pos	Flat	3237 × g	
	96/384 wells			4500 rpm	
		5910 752.008			
	1/4	(without upper part)	? mm/64 mm	14.4 cm	
	Deepwell plate	party	Flat	3237 × g	
	96 wells			4500 rpm	
		5910 752.008			
	1/4	(without upper	2 // 4	142	
	1/4 Conical tube	part)	? mm/64 mm Conical	14.3 cm	
	50 mL		Ø 29 mm	4347 × <i>g</i> 4500 rpm	
	9/36	5910 769.008	(Load 5 inner bores only)/116 mm	19.2 cm	
	Microplate	1698	Flat	2604 × g	
	96/384 wells			4500 rpm	
	1/4	5910 769.008	16 mm/??16 mm	11.5 cm	
	Round-bottom tube 7.5 mL – 12 mL (Ø 16 × 75 mm – 100 mm)		Round Ø 16 mm	4302 × g	
	Ø 16 mm			4500 rpm	
	26/104	5910 754.000	118 mm/120 mm	19.0 cm	
F	Tube		Round	4256 × g	
	9 mL (Ø 17.5 mm × 100 mm)		Ø 17.5 mm	4500 rpm	
	21/84	5910 762.003	118 mm/120 mm	18.8 cm	

Tube	Tube	Adapter	Bottom shape	Max. g-force
	Capacity		Diameter	Max. speed
	Number per adapter/rotor	Order no. (international)	Max. tube length with/without cap	Radius
	Round-bottom tube 4 mL – 8 mL (Ø 13 × 75 mm – 100 mm)		Round Ø 13 mm	4302 × <i>g</i> 4500 rpm
0 0 1	30/120	5910 755.007	117 mm/119 mm	19.0 cm
	Conical tube 500 mL Corning		Conical Ø 96 mm	4234 × <i>g</i> 4500 rpm
	1/4	5910 760.000	–/148 mm	18.7 cm
	Wide-neck bottle 750 mL		Flat Ø 102 mm	4256 × <i>g</i> 4500 rpm
	1/4	5910 757.000	135 mm/139 mm	18.8 cm
	Wide-neck bottle		Flat	44569 × g
	1000 mL		Ø 119 mm	4256 rpm
	1/4	5910 756.003	132 mm/138 mm	18.8 cm

# 14.1.2 Swing-bucket rotor S-4×Universal with 4 universal buckets and a plate carrier

Always use the plate carrier for centrifugation of the following plates and tubes. Use a plate carrier and an adapter if necessary.

510			Max. g-force:	3849 × g	
			Max. speed:	4500 rpm	
Rotor S-4×Universal	Universal bucket with plate carrier		Max. load per 1 595 g bucket (adapter, tube and contents):		
Plate/tube	Plate	Adapter	Bottom shape	Max. g-force	
	Capacity			Max. speed	
	Number per adapter/rotor	Order no. (international)	Max. loading height with/ without cap	Radius	
	Microplate	(1)	Flat	3849 × g	
	96/384 wells			4500 rpm	
	5/20	5910 753.004	66 mm/80 mm	17.0 cm	
	Deepwell plate		Flat	3849 × g	
	96 wells			4500 rpm	
	1/4	5910 753.004	66 mm/80 mm	17.0 cm	
	Cell-culture plate		Flat	3849 × g	
				4500 rpm	
	1/4	5910 753.004	66 mm/80 mm	17.0 cm	
	Kit		Flat	3849 × g	
				4500 rpm	
	1/4	5910 753.004	–/80 mm	17.0 cm	
B	PCR plate	Plate carrier +	Flat	3645 × g	
	384 wells			4500 rpm	
	1/4	5825 713.001	66 mm/80 mm	16.1 cm	

Plate/tube	Plate	Adapter	Bottom shape	Max. g-force
	Capacity			Max. speed
	Number per adapter/rotor	Order no. (international)	Max. loading height with/ without cap	Radius
	PCR plate	Plate carrier +	Conical	3690 × g
- www.	96 wells			4500 rpm
	1/4	5825 711.009	66 mm/80 mm	16.3 cm
Slide	CombiSlide	Plate carrier +	Flat	3758 × g
	12 slides			4500 rpm
	12/48	5825 706.005	66 mm/80 mm	16.6 cm
	IsoRack	Plate carrier +	Open	3690 × g
	24 × 0.5 mL micro test tubes		Ø 6 mm	4500 rpm
	1/4	5825 708.008	66 mm/80 mm	16.3 cm
<b>D</b>	IsoRack	Plate carrier +	Open	3600 × g
	24 × 1.5/2 mL micro test tubes		Ø 11 mm	4500 rpm
	1/4	5825 709.004	66 mm/80 mm	15.9 cm

# 14.2 Rotor S-4×750

# 14.2.1 Swing-bucket rotor S-4×750 with 4 750 mL round buckets

## Influence of speed on the temperature with device version 120 V

To safely maintain a temperature of 4 °C at an ambient temperature of 23 °C, the speed must be reduced to 4400 rpm.

Rotational speed			Temperature			
4400 rpm			≤4°C			
4700 rpm			≤6°C			
			Max. g-force:  Max. rotational	100 V: 4031 × <i>g</i> 100 V:	120 V/230 V: 4816 × g 120 V/230:	
			speed:	4300 rpm	4700 rpm	
Rotor S-4×750	Round bucket 750 mL	Aerosol-tight cap	Max. load per bucket (adapter, tube and contents):	1000 g	1000 g	
Tube	Tube	Adapter	Bottom shape		Max. g-force	
Tube	Capacity	Adapter	Tube diameter		Max. rotational	
	Capacity		Tube diameter		speed	
			Max. tube		Radius	
	Tubes per adapter/rotor	Order no. (international)	length with/ without cap	100 V	120 V/230 V	
	Micro test tube		Open	Top: $3059 \times g$ Bottom: $4010 \times g$	Top: $3655 \times g$ Bottom: $4791 \times g$	
	1.5 mL/2 mL	000	Ø 11 mm	4300 rpm	4700 rpm	
	50/200	5825 740 009	39 mm	Top: 14.8 cm Bottom: 19.4 c	Top: 14.8 cm Bottom: 19.4 c	
		3823 740 009		m	m	
	Round-bottom tube Ø 12 mm × 75 mm		Round Ø 12 mm	3845 × <i>g</i> 4300 rpm	4594 × <i>g</i> 4700 rpm	
	27/108	5825 747 003	113 mm/ 120 mm	18.6 cm	18.6 cm	

Tube	Tube	Adapter	Bottom shape		Max. g-force
	Capacity		Tube diameter		Max. rotational speed
			Max. tube		Radius
	Tubes per adapter/rotor	Order no. (international)	length with/ without cap	100 V	120 V/230 V
	Round-bottom tube		Round	3824 × g	4569 × g
U U	4 mL - 8 mL (Ø 13 mm × 75 mm - 100 mm)		Ø 13 mm	4300 rpm	4700 rpm
	23/92	5825 738 004	113 mm/ 121 mm	18.5 cm	18.5 cm
	Eppendorf Tubes		Conical	3886 × g	4643 × g
	5 mL		Ø 17 mm	4300 rpm	4700 rpm
	14/56	5825 734 009 (without upper part)	65 mm	18.8 cm	18.8 cm
	Round-bottom	1 1	Round	3845 × g	4594 × g
	tube 7.5 mL – 12 mL (Ø 16 mm × 75 mm – 100 mm)		Ø 16 mm	4300 rpm	4700 rpm
	20/80	5825 736 001	120 mm/ 125 mm	18.6 cm	18.6 cm
F P	Round-bottom		Round	3845 × g	4594 × g
	tube 8 mL – 16 mL		Ø 16 mm	4300 rpm	4700 rpm
	7/28 (Load inner bores only (see p. 32))	5825 736 001	(Do not use an aerosol-tight cap.)/125 mm	18.6 cm	18.6 cm
Å	Tube		Round	3824 × g	4569 × g
	9 mL (Ø 17.5 mm × 100 mm)		Ø 17.5 mm	4300 rpm	4700 rpm
	20/80	5825 743 008	112 mm/ 117 mm	18.5 cm	18.5 cm

Tube	Tube	Adapter	Bottom shape		Max. g-force
	Capacity		Tube diameter		Max. rotational
			Many Author		speed
	Tubes per	Order no.	Max. tube length with/	100 V	Radius 120 V/230 V
	adapter/rotor	(international)	without cap	100 V	120 V/230 V
	Round-bottom tube		Round	3824 × g	4569 × g
зпаницанна)	14 mL		Ø 17.5 mm	4300 rpm	4700 rpm
	14/56	5825 748 000	106 mm	18.5 cm	18.5 cm
	Conical tube	c to	Conical	3886 × g	4643 × g
Thomannanna (T)	15 mL		Ø 17 mm × 104 mm	4300 rpm	4700 rpm
	14/56	5825 734 009	120 mm/ 125 mm	18.8 cm	18.8 cm
	Conical tube	L-1	Conical	3742 × g	4470 × g
	(skirted) 30 mL		Ø 25 mm	4300 rpm	4700 rpm
		5825 755 006	114 mm/ 119 mm	18.1 cm	18.1 cm
	Conical tube		Conical	3866 × g	4618 × g
	50 mL		Ø 29 mm	4300 rpm	4700 rpm
	7/28	5825 733 002	116 mm/ 122 mm	18.7 cm	18.7 cm
	Conical tube		Conical	3659 × g	4371 × g
	(skirted) 50 mL	propode	Ø 29 mm	4300 rpm	4700 rpm
	5/20	5825 732 006	116 mm/ 122 mm	17.7 cm	17.7 cm
	Wide-neck bottle/conical tube		Flat	3786 × g	4519 × <i>g</i>
— v	175 mL – 250 mL		Ø 62 mm	4300 rpm	4700 rpm
	1/4	5825 741 005	125 mm/ 145 mm	18.3 cm	18.3 cm

Tube	Tube	Adapter	Bottom shape		Max. g-force
	Capacity		Tube diameter		Max. rotational speed
			Max. tube		Radius
	Tubes per adapter/rotor	Order no. (international)	length with/ without cap	100 V	120 V/230 V
	Conical tube	A	Conical	3845 × g	4594 × g
	500 mL Corning		Ø 96 mm	4300 rpm	4700 rpm
	1/4	5825 745 000	(Do not use an aerosol-tight cap.)/147 mm	18.6 cm	18.6 cm
Minnanin	Wide-neck bottle		Flat	3824 × g	4569 × g
	750 mL		Ø 102 mm	4300 rpm	4700 rpm
	1/4	5825 744 004	150 mm/ 150 mm	18.5 cm	18.5 cm

# 14.2.2 Swing-bucket rotor S-4×750 with 4 plate buckets

Always use the plate carrier for centrifugation of the following plates and tubes. Use a plate carrier and adapter if necessary.

	Canacity			May r	haara lenaad
Plate	Plate	Adapter	Bottom shape		Max. g-force
Kotor 5-4×/50	(always use with a plate carrier)	Aerosol-tight cap	Max. load per bucket (adapter, tube and contents):	450 g	450 g
Rotor S-4×750	Plate bucket	A aracal tight	<u>'</u>	·	<u>'</u>
			Max. rotational speed:	100 V: 4300 rpm	120 V/230: 4700 rpm
				$3328 \times g$	$3976 \times g$
An nA			Max. g-force:	100 V:	120 V/230 V:

Plate	Plate	Adapter	Bottom shape		Max. g-force
	Capacity			Max. rotational spee	
	Number per adapter/rotor	Order no. (international)	Max. loading height		Radius
				100 V	120 V/230 V
	Microplate		Flat	$3328 \times g$	$3976 \times g$
	96/384 wells			4300 rpm	4700 rpm
	4/16	5820 756 004	47 mm/64 mm	16.1 cm	16.1 cm
	Deepwell plate	<u></u>	Flat	3328 × g	3976 × g
	96 wells			4300 rpm	4700 rpm
	1/4	5820 756 004	47 mm/64 mm	16.1 cm	16.1 cm
	Cell-culture	M	Flat	3328 × g	3976 × g
	plate			4300 rpm	4700 rpm
	2/8	5820 756 004	47 mm/64 mm	16.1 cm	16.1 cm
	Kit	<u></u>	Flat	3328 × g	3976 × g
				4300 rpm	4700 rpm
	1/4	5820 756 004	47 mm/64 mm	16.1 cm	16.1 cm
2	IsoRack	Plate carrier +	Open	3183 × g	3803 × g
	24 × 0.5 mL micro test tubes		Ø 6 mm	4300 rpm	4700 rpm
	1/4	5825 708 008	47 mm/64 mm	15.4 cm	15.4 cm

Plate	Plate	Adapter	Bottom shape		Max. g-force
	Capacity			Ma	x. rotational speed
	Number per adapter/rotor	Order no. (international)	Max. loading height		Radius
8	IsoRack	Plate carrier +	Open	3101 × g	3704 × g
Ţ	24 × 1.5/2 mL micro test tubes		Ø 11 mm	4300 rpm	4700 rpm
	1/4	5825 709 004	47 mm/64 mm	15.0 cm	15.0 cm
	PCR plate	Plate carrier +	Flat	3142 × g	3754 × g
	384 wells			4300 rpm	4700 rpm
	1/4	5825 713 001	47 mm/64 mm	15.2 cm	15.2 cm
	PCR plate	Plate carrier +	Conical	3183 × g	3803 × g
vooroopp .	96 wells			4300 rpm	4700 rpm
	1/4	5825 711 009	47 mm/64 mm	15.4 cm	15.4 cm
Slide	CombiSlide	Plate carrier +	Flat	3245 × g	3877 × g
	12 slides			4300 rpm	4700 rpm
	12/48	5825 706 005	47 mm/64 mm	15.7 cm	15.7 cm

# 14.3 Rotor S-4×500

# 14.3.1 Swing-bucket rotor S-4×500 with 4 500 mL rectangular buckets

			Max. <i>g-force</i> :  Max. rotational speed:	3220 × g 4000 r pm
Rotor S-4×500	Rectangular bucket 500 mL	Aerosol-tight cap	Max. load per bucket (adapter, tube and contents):	780 g

# 14.3.2 Swing-bucket rotor S-4x500 with 4 MTP/Flex buckets

	<u> </u>	Max. g-force:	2900 × g
		Max. rotational speed:	4000 rpm
Rotor S-4×500	MTP/Flex buckets	Max. load per bucket (adapter, tube and contents):	380 g

## 14.4 Rotor S-4×400

		_	Max. g-force:	5263 × g
			Max. speed:	5100 rpm
Rotor S-4×400	Round bucket 400 mL	Aerosol-tight cap	Max. load per bucket (adapter, tube and contents):	570 g
Tube	Tube	Adapter	Bottom shape	Max. g-force
	Capacity		Diameter	Max. speed
	Tubes per adapter/rotor	Order no. (international)	Max. tube length with/without cap	Radius
	Micro test tube		Open	Top: $3897 \times g$ Bottom: $5147 \times g$
$\nabla$	1.5 mL/2 mL	T P P P P P P P P P P P P P P P P P P P	Ø 11 mm	5100 rpm
	26/104	5910 708.009	39 mm	Top: 13.4 cm Bottom: 17.7 cm
	Round-bottom tube	A	Round	5002 × g
	Ø 12 mm × 75 mm		Ø 12 mm	5100 rpm
	17/68	5910 711.000	112 mm/118 mm	17.2 cm
	Round-bottom tube	A	Round	4973 × g
	4 mL – 8 mL (Ø 13 mm × 75 mm – 100 mm)		Ø 13 mm	5100 rpm
	15/60	5910 703.007	105 mm/119 mm	17.1 cm
	Round-bottom tube	A A	Round	5031 × g
	7.5 mL – 12 mL (Ø 16 mm × 75 mm – 100 mm)		Ø 16 mm	5100 rpm
	11/44	5910 704.003	115 mm/122 mm	17.3 cm

Tube	Tube	Adapter	Bottom shape	Max. g-force
	Capacity		Diameter	Max. speed
	Tubes per adapter/ rotor	Order no. (international)	Max. tube length with/without cap	Radius
	Round-bottom tube	A	Round	5031 × g
	9 mL (Ø 17.5 mm × 100 mm)		Ø 17.5 mm	5100 rpm
	8/32	5910 709.005	115 mm/122 mm	17.3 cm
	Eppendorf Tubes		Conical	5234 × g
	5 mL	5910 702.000	Ø 17 mm	5100 rpm
	7/20	(without upper	127 /122	10.0
	7/28	part)	126 mm/133 mm	18.0 cm
	Conical tube 15 mL		Ø 17 mm	5234 × <i>g</i> 5100 rpm
	7/28	5910 702.000	126 mm/133 mm	18.0 cm
	Conical tube	A	Conical	5205 × g
	50 mL		Ø 29 mm	5100 rpm
	4/16	5910 701.004	117 mm/125 mm	17.9 cm
	Conical tube (skirted)		Conical	4943 × g
	50 mL		Ø 29 mm	5100 rpm
	3/12	5910 712.006	120.5 mm/122 mm	17.0 cm

Tube	Tube	Adapter	Bottom shape	Max. g-force
	Capacity		Diameter	Max. speed
	Tubes per adapter/ rotor	Order no. (international)	Max. tube length with/without cap	Radius
	Wide-neck bottle/ conical tube 175 mL – 250 mL	The second secon	Flat For conical tubes, additionally use the manufacturer's adapter. Ø 62 mm	5060 × <i>g</i> 5100 rpm
	1/4	5910 705.000	129 mm/138 mm	17.4 cm
	Conical tube		Conical	5263 × g
	175 mL – 225 mL		Ø 62 mm	5100 rpm
	1/4	5910 714.009	137 mm/143 mm	18.1 cm
	Wide-neck bottle		Flat	5030 × g
-	400 mL (gray lid)		Ø 62 mm	5100 rpm
Eppendorf	1/4		121 mm/129 mm	17.3 cm
		5910 706.006		

## 14.5 Rotor FA-6×50

Aerosol-tight fixed-angle rotor for 6 conical tubes

	Max. g-force:	20130 × g
	Max. rotational speed:	12100 rpm
Rotor FA-6×50	Max. load (adapter, tube and contents):	6 × 75 g

Tube	Tube	Adapter	Bottom shape	Max. g-force
	Capacity	Order no. (international)	Tube diameter	Max. rotational speed
	Tubes per adapter/ rotor		Max. tube length with rotor lid	Radius
	Round-bottom tube	ı	Round	19642 × g
	16 mL	() Johnsondon	Ø 18.1 mm	12100 rpm
	1/6	5820 720 000	107 mm	12.0 cm
n n	Round-bottom tube		Round	19642 × g
	2.6 mL – 5 mL (Ø 13 mm × 75 mm)		Ø 13.5 mm	12100 rpm
0 0	1/6	5820 726 008	_	12.0 cm
A 44 E	Round-bottom tube		Round	19642 × g
	4 mL - 8 mL (Ø 13 mm × 100 mm)	1020 725 001	Ø 13.5 mm	12100 rpm
	1/6	5820 725 001	119 mm	12.0 cm
M	Eppendorf Tubes	1	Conical	19806 × g
	5 mL		Ø 17 mm	12100 rpm
# <u>-</u>	1/6	5820 730 005	_	12.1 cm
	Round-bottom tube	Î	Round	19642 × g
	5.5 mL – 10 mL (Ø 16 mm × 75 mm)		Ø 16 mm	12100 rpm
	1/6	5820 728 000	_	12.0 cm

Tube	Tube	Adapter	Bottom shape	Max. g-force
	Capacity	Order no. (international)	Tube diameter	Max. rotational speed
	Tubes per adapter/ rotor		Max. tube length with rotor lid	Radius
	Round-bottom tube		Round	19642 × g
	7.5 mL – 12 mL (Ø 16 mm × 100 mm)	() proposedate	Ø 16.4 mm	12100 rpm
	1/6	5820 727 004	119 mm	12.0 cm
- A	Tube	ı	Round	19642 × g
	9 mL	O constant	Ø 16.4 mm	12100 rpm
ų.	1/6	adds.	112 mm	12.0 cm
		5820 729 007		
iii	Conical tube		Conical	19642 × g
Total transfer of the state of	15 mL		Ø 17 mm	12100 rpm
J	1/6	5820 717 009	125 mm	12.0 cm
	Round-bottom tube	9	Round	17187 × g
	30 mL	papasdih	Ø 25.7 mm	12100 rpm
U	1/6	5820 721 006	104 mm	10.5 cm
	Conical tube		Conical	18333 × g
luduludud	35 mL	5820 722 002	Ø 28.7 mm	12100 rpm
V	1/6	3820 722 002	113 mm	11.2 cm
	Conical tube	-	Conical	20133 × g
	50 mL		Ø 29.6 mm	12100 rpm
	1/6		127 mm	12.3 cm

## 14.6 Rotor FA-20×5

Aerosol-tight fixed-angle rotor for 20 tubes

6000	Max. g-force:	20913 × g
	Max. rotational speed:	13100 rpm
Rotor FA-20×5	Max. load (adapter, tube and contents):	20 × 9.5 g

Tube	Tube	Adapter	Bottom shape	Max. g-force
	Capacity	Order no. (international)	Tube diameter	Max. rotational speed
	Tubes per adapter/ rotor			Radius
	HPLC vial	9		17076 × g
			Ø 11 mm	13100 rpm
	1/20	5820 770 007		8.9 cm
<b>B</b>	Cryogenic tube	9		18802 × g
JZ	1.0 mL/2.0 mL		Ø 13 mm	13100 rpm
	1/20	5820 769 009		9.8 cm
8	Micro test tube	9	Open	18227 × g
	1.5 mL/2.0 mL		Ø 11 mm	13100 rpm
$\forall$	1/20	5820 768 002		9.5 cm
	Eppendorf Tubes		Conical	20913 × g
	5 mL		Ø 17 mm	13100 rpm
	<b>-/20</b>			10.9 cm

## 14.7 Rotor FA-48×2

Aerosol-tight fixed-angle rotor for 48 micro test tubes

	Max. <i>g-force</i> : Outer ring Inner ring	22132 × <i>g</i> 19502 × <i>g</i>
	Max. rotational speed:	14000 rpm
Rotor FA-48×2	Max. load (adapter, tube and contents):	48 × 3.75 g

Tube	Tube	Adapter	Bottom shape	Max. g-force Outer ring Inner ring
	Capacity		Tube diameter	Max. rotational speed
	Tubes per adapter/rotor	Order no. (international)		Radius Outer ring Inner ring
	PCR tube	0	Conical	17530 × <i>g</i> 14901 × <i>g</i>
	0.2 mL		Ø 6 mm	14000 rpm
	1/48	5425 715.005		8 cm 6.8 cm
	Micro test tube	å	Conical	22132 × <i>g</i> 19502 × <i>g</i>
V	0.4 mL	Ш	Ø 6 mm	14000 rpm
	1/48	5425 717.008		10.1 cm 8.9 cm
	Micro test tube	8	-	19722 × <i>g</i> 17092 × <i>g</i>
V	0.5 mL	U	Ø 8 mm	14000 rpm
	1/48	5425 716.001		9 cm 7.8 cm
A	Microtainers		_	22132 × <i>g</i> 19502 × <i>g</i>
U	0.6 mL	U	Ø 8 mm	14000 rpm
	1/48	5425 716.001		10.1 cm 8.9 cm

Tube	Tube	Adapter	Bottom shape	Max. <i>g</i> -force Outer ring Inner ring
	Capacity		Tube diameter	Max. rotational speed
	Tubes per adapter/	Order no. (international)		Radius Outer ring Inner ring
	Micro test tube		Round	22132 × <i>g</i> 19502 × <i>g</i>
$\bigvee$	1.5 mL/2 mL		Ø 11 mm	14000 rpm
	<b>-/48</b>			10.1 cm 8.9 cm

## 14.8 Rotor FA-30×2

Aerosol-tight fixed-angle rotor for 30 micro test tubes

(65000)	Max. g-force:	20984 × g
	Max. rotational speed:	13700 rpm
Rotor FA-30×2	Max. load (adapter, tube and contents):	30 × 3.5 g

Tube	Tube	Adapter	Bottom shape	Max. g-force
	Capacity		Tube diameter	Max. rotational
	<b>T</b> 1			speed
	Tubes per adapter/ rotor	Order no. (international)		Radius
<u> </u>	Micro test tube	_	_	20984 × g
	1.5/2 mL		Ø 11 mm	13700 rpm
V	<b>-/30</b>			10.0 cm
<u>8</u>	PCR tube	0	Conical	15948 × g
A	0.2 mL		Ø 6 mm	13700 rpm
	1/30	5425 715.005		7.6 cm
<b>5</b> 3	Micro test tube	8	Conical	20817 × g
	0.4 mL		Ø 6 mm	13700 rpm
	1/30	5425 717.008		9.7 cm
2	Micro test tube	8	Open	18400 × g
$\forall$	0.5 mL		Ø 8 mm	13700 rpm
	1/30	5425 716.001		8.6 cm
<u> </u>	Microtainers	8	Open	20817 × g
	0.6 mL		Ø 8 mm	13700 rpm
	1/30	5425 716.001		9.7 cm

## 14.9 Rotor FA-6x250

Required software version 1.5

	Max. g-force:	15050 x <i>g</i>
	Max. rotational speed:	10100 rpm
FA-6x250	Max. load per bucket (adapter, tube and contents):	6 x 365 g

Tube	Tube	Adapter	Bottom shape	Max. g-force
	Capacity		Tube diameter	Max. rotational speed
	Number per adapter/rotor	Order no. (international)	Max. tube length	Radius
	Round-bottom tube	1	Round	14370 × g
	Ø 12 mm × 75 mm		Ø 12 mm	10100 rpm
	9/54	5920 765 000	114 mm	12.6 cm
	Round-bottom tube	1 1	Round	14256 × g
	4 mL - 8 mL (Ø 13 × 75 mm - 100 mm)		Ø 13 mm	10100 rpm
	8/48	5920 763 008	114 mm	12.5 cm
	Round-bottom tube 7.5 mL – 12 mL (Ø 16 × 75 mm – 100 mm)		Round Ø 16 mm	14256 × <i>g</i> 10100 rpm
	7/42	5920 762 001	115 mm	12.5 cm

Tube	Tube	Adapter	Bottom shape	Max. g-force
	Capacity		Tube diameter	Max. rotational speed
	Number per adapter/rotor	Order no. (international)	Max. tube length	Radius
Ā	Tube	ı	Round	14370 × g
	9 mL (Ø 17.5 mm × 100 mm)		Ø 17.5 mm	10100 rpm
	7/42	5920 764 004	112 mm	12.6 cm
	Conical tube	(00)	Conical	13686 × g
1040000000 <u>(T</u> )	15 mL		Ø 17 mm	10100 rpm
	4/24	5920 761 005	122 mm	12 cm
	Conical tube		Conical	12545 × g
	50 mL		Ø 30 mm	10100 rpm
	1/6	5920 760 009	125 mm	11 cm
	Conical tube (skirted)		Conical, skirted	12317 × g
	50 mL		Ø 30 mm	10100 rpm
	1/6	5920 766 007	125 mm	10.8 cm
	Round-bottom tube	1	Round	14370 × g
шининентий)	10 mL		Ø 17 mm	10100 rpm
	7/42	5920 769 006	115 mm	12.6 cm

Tube	Tube	Adapter	<b>Bottom shape</b>	Max. g-force
	Capacity		Tube diameter	Max. rotational
	Number per adapter/rotor	Order no. (international)	Max. tube length	speed Radius
	Round-bottom tube		Round	14370 × g
(Hondingtonian	16 mL		Ø 18 mm	10100 rpm
-	7/42	5920 770 004	115 mm	12.6 cm
	Round-bottom tube	A	Round	14256 × g
	30 mL		Ø 26 mm	10100 rpm
	3/18	5920 767 003	116 mm	12.5 cm
	Round-bottom tube		Round	12659 × g
	50 mL		Ø 29 mm	10100 rpm
	1/6	5920 771 000	125 mm	11.1 cm
	Round-bottom tube		Round	12887 × g
	85 mL		Ø 38 mm	10100 rpm
	1/6	5920 768 000	118 mm	11.3 cm
	Wide-neck bottle		Flat	15054 × g
	250 mL flat		Ø 62 mm	10100 rpm
	6		135 mm	13.2 cm

## 14.10 Rotor F-48×15

Fixed-angle rotor with 48 steel cores

	Max. g-force	$5005 \times g$
	Max. rotational speed	5500 rpm
Rotor F-48×15	Max. load (sleeve, adapter, tube and contents)	48 × 56 g

Rotors for the Centrifuge 5910 Ri Centrifuge 5910 Ri English (EN)

122

## 15 Ordering information

## 15.1 Rotors and accessories

The order numbers for the adapters can be found in the "Rotors for Centrifuge 5910 R" chapter (see p. 97).

### 15.1.1 Rotor S-4×Universal

Order no.	Description
(International)	
	Rotor S-4×Universal
5895 200.001	incl. universal buckets
	Adapter
	for 25/50 mL conical tubes, 175-250 mL bottles and plates, for S-4xUniversal rotor
5910 751.001	set with 2 pieces
	Adapter
	for 5/15 mL conical tubes and plates, for rotor S-4xUniversal
5910 752.008	set with 2 pieces
	Adapter
	for 5 MTP, DWP, PCR Platten, for rotor S-4×Universal
5910 753.004	set of 2
	Adapter
	for 26 x 7,5 mL - 12 mL round-bottom tubes, for rotor S-4×Universal
5910 754.000	set of 2
	Adapter
	for 30 round-bottom tubes 4 mL - 8 mL, for rotor S-4×universal
5910 755.007	set of 2
	Adapter
	1000 mL, flat bottom, for rotor S-4×universal, set of 2
5910 756.003	for 1000 mL wide-neck bottle, 2 pieces
	Adapter
	750 mL, bottle, for rotor S-4×universal
5910 757.000	set of 2
	Adapter
	für 46 Tubes 12 x 75 mm, 5 mL FACS, for rotor S-4×Universal
5910 758.006	set of 2
	Adapter
	for 21 x 9 mL tubes, for rotor S-4×Universal
5910 762.003	set of 2
	Adapter
	for 7 x 50 mL conical tubes, skirted, for rotor S-4xUniversal
5910 764.006	set of 2
	Adapter
	for 25/50 mL conical tubes and plates, for rotor S-4xUniversal
5910 769.008	set with 2 pieces

#### 15.1.2 Rotor S-4×750

Order no.	Description	
(International)		
	Rotor S-4×750	
5895 120.008	incl. round bucket	
	Round bucket S-4×750	
5895 123.007	2 pieces	
5895 122.000	4 pieces	
	Aerosol-tight cap	
	Rotors S-4-104, S-4×750, S-4×1000, round bucket 750 mL/1000 mL	
5820 747.005	2 pieces	
	Sealings for aerosol-tight caps	
	Rotors S-4-104, S-4×750, S-4×1000, round bucket 750 mL/1000 mL	
5820 749.008	5 pieces	
	Sealings for aerosol-tight caps	
	Rotor S-4×Universal-Large, rotor S-4×universal, universal buckets	
5920 754.009	5 pieces	

Order no.	Description	
(International)		
	Rotor S-4×750	
5895 128.009	incl. plate bucket	
	Plate bucket (aerosol-tight capable)	
	for Rotor S-4×750	
5895 125.000	2 pieces	
5895 124.003	4 pieces	
	Aerosol-tight cap	
	Rotors S-4-104, S-4x750, Plate Bucket	
5820 748.001	2 pieces	
	Sealings for aerosol-tight caps	
	Rotors S-4-104, S-4×750, S-4×1000, Plate/Tube Bucket	
5820 780.002	4 pieces	
	Plate carrier	
	Rotor S-4-104, S-4×750	
5820 756.004	2 pieces	

#### 15.1.3 Rotor S-4×500

Order no.	Description	
(International)		
	Rotor S-4x500	
	for 500 mL rectangular buckets or MTP/Flex-buckets	
5895 170.005	incl. 4 × 500 mL rectangular buckets	
5895 171.001	without bucket	
	Rectangular bucket 500 mL	
5810 730.007	Set of 4	
	MTP/Flex buckets	
	for use with IsoRack and cell culture flask adapters as well as MTP and DWP	
5810 742.005	2 pieces	
5810 741.009	4 pieces	

### 15.1.4 Rotor S-4×400

Order no.	Description	
(International)		
	Rotor S-4×400	
5895 180.000	incl. round bucket 400 mL	
5895 181.007	without bucket	
	Round bucket S-4×400	
5895 183.000	2 pieces	
5895 182.003	4 pieces	
	Aerosol-tight cap	
	Rotor S-4×400, round buckets 400 mL	
5910 700.008	2 pieces	
	Sealings for aerosol-tight caps	
	Rotor S-4×400, r ound buckets 400 mL	
5910 710.003	2 pieces	

## 15.1.5 Rotor FA-6×50

Order no.	Description
(International)	
	Rotor FA-6×50
	aerosol-tight, 6 × 50 mL conical tubes
5895 150.004	incl. aerosol-tight rotor lid
	Rotor lid FA-6x50
5895 151.000	aerosol-tight, aluminum
	Seal for rotor lid
	FA-45-18-11 (5418/5418 R), FA-45-6-30 (5804/5804 R/5810/5810 R), FA-6×50
	(5910 R, 5920 R)
5418 709.008	5 pieces

### 15.1.6 Rotor FA-20×5

Order no.	Description					
(International)						
	Rotor FA-20×5					
	aerosol-tight, 20 × 5 mL tubes					
5895 130.003	incl. aerosol-tight rotor lid					
	Rotor lid FA-20×5					
5895 131.000	aerosol-tight, aluminum					
	Seal for rotor lid					
	FA-45-20-17 (5804/5804 R/5810/5810 R), FA-20x5 (5910 R, 5920 R)					
5409 718.002	5 pieces					

#### 15.1.7 Rotor FA-48×2

Order no.	Description				
(International)					
	Rotor FA-48×2				
	aerosol-tight, 48 × 1,5/2 mL tubes				
5895 135.005	incl. aerosol-tight rotor lid				
	Rotor lid FA-48×2				
5895 136.001	aerosol-tight, aluminum				
	Seal for rotor lid				
	FA-45-24-11-Kit (5427 R/530/5430 R), FA-45-48-11 (5427 R/5430/5430 R, 5804/				
	5804 R/5810/5810 R), FA-30x2 (5910 R, 5920 R), FA-48x2 (5910 R, 5920 R)				
5820 767.006	5 pieces				

### 15.1.8 Rotor FA-30×2

Order no.	Description					
(International)						
	Rotor FA-30×2					
	aerosol-tight, 30 × 1,5/2 mL tubes					
5895 155.006	incl. aerosol-tight rotor lid					
	Rotor lid FA-30×2					
5895 156.002	aerosol-tight, aluminum					
	Seal for rotor lid					
	FA-45-24-11-Kit (5427 R/530/5430 R), FA-45-48-11 (5427 R/5430/5430 R, 5804/					
	5804 R/5810/5810 R), FA-30x2 (5910 R, 5920 R), FA-48x2 (5910 R, 5920 R)					
5820 767.006	5 pieces					

### 15.1.9 Rotor F-48×15

Order no.	Description				
(International)					
	Rotor F-48×15				
	for 48 × 15 mL conical tubes				
5895 160.000	incl. 48 steel sleeves and adapters				
	Steel sleeves and adapter				
	for vessels 15 mL				
5820 774.002	for rotors F-35-48-17 (5804/5804 R/5810/5810 R) , F-48×15 (5910 R) (5804/5804 R/				
	5810/5810 R) , F-48×15 (5910 R)				

### 15.1.10 Rotor FA-6x250

Order no.	Description					
(International)						
	FA-6x250 rotor					
	for 6 x 250 mL tubes, incl. QuickLock rotor cover, aerosol-tight, Centrifuge 5910 R/					
	5920 R					
5895 175.007						
	QuickLock rotor cover					
	aerosol-tight, replacement part for FA-6x250 rotor					
5895 176.003						
	Seal for rotor lid					
5895 177.000	5 pieces					

## 15.2 Accessories

Order no.	Description
(International)	
	Rotor key
0113 005.106	
	Mains/power cord
0113 204.486	230 V/50 Hz, Europe
0113 204.680	230 V/50 Hz, GB/HK
0013 613.953	230 V/50 Hz, CN
0113 204.699	230 V/50 Hz, AUS
0113 205.105	230 V/50 Hz, ARG
	Pivot grease
5810 350.050	Tube 20 mL

**Ordering information** Centrifuge 5910 Ri English (EN)

128



# **Declaration of Conformity**

The product named below fulfills the requirements of directives and standards listed. In the case of unauthorized modifications to the product or an unintended use this declaration becomes invalid. This declaration of conformity is issued under the sole responsibility of the manufacturer.

#### **Product name:**

Centrifuge 5910 Ri

including components

#### Product type:

Centrifuge

#### Relevant directives / standards:

2006/42/EC: EN ISO 12100, EN 378-1, EN 378-2, EN IEC 61010-2-120

2014/35/EU: EN 61010-1, EN 61010-2-011, EN 61010-2-020, IEC 61010-1, IEC 61010-2-011,

IEC 61010-2-020, IEC 61010-2-101

EN 61326-1, EN 55011, IEC 61326-1, CISPR 11

UL 61010-1, UL 61010-2-020

CAN/CSA C22.2 No. 61010-1, CAN/CSA C22.2 No. 61010-2-020

47 CFR FCC part 15

2011/65/EU: EN 50581

Person authorized to compile

the technical file acc. to 2006/42/EC: Dr. Marlene Jentzsch

Head of Business Unit Separation

**Eppendorf AG** 

Hamburg, October 06, 2020

2014/30/EU:

Dr. Wilhelm Plüster Management Board Dr Marlene Jentzsch Head of Business Unit Separation

Your local distributor: www.eppendorf.com/contact Eppendorf AG · Barkhausenweg 1 · 22339 Hamburg · Germany eppendorf@eppendorf.com ISO 9001 Certified

ISO 13485 Certified ISO 14001 Certified

eppendorf@eppendorf.com
Eppendorf\* and the Eppendorf Brand Design are registered trademarks of Eppendorf AG, Germany.
All rights reserved, incl. graphics and pictures. Copyright @2020 by Eppendorf AG.



# **Certificate of Containment Testing**

Containment Testing of Caps (5820 741.309-00) for Rotor S-4x750 with Roundbuckets (5895 102.115-00) in the Eppendorf 5920/R Bench Top Centrifuge

Report No. 14/014

Report Prepared For: Eppendorf AG, Hamburg, Germany

Issue Date:

26<sup>th</sup> June 2014

## **Test Summary**

Caps (5820 741.309-00) for rotor S-4x750 with Roundbuckets (5895 102.115-00) were containment tested in the Eppendorf 5920/R bench top centrifuge, using Annex AA of IEC 61010-2-020:2006 (2<sup>nd</sup> Ed.). The sealed rotor was shown to contain a spill within the centrifuge.

Report Written By

Name: Mr Matthew Hewitt

Title: Biosafety Scientist

Report Authorised By

Name: Mrs Sara Speight

Title: Senior Biosafety Scientist



# **Certificate of Containment Testing**

**Containment Testing of Rotor S-4x750** (5895 120.105-00) with Plate Buckets (5895 124.119-00\*) and Caps (5820 743.301-00#) in an Eppendorf Bench **Top Centrifuge** 

Report No. 14/043 A

Report Prepared For: Eppendorf AG, Hamburg, Germany

17<sup>th</sup> February 2015 Issue Date:

## **Test Summary**

Rotor S-4x750 (5895 120.105-00) with Plate Buckets (5895 124.119-00\*) and Caps (5820 743.301-00#) was containment tested in an Eppendorf bench top centrifuge, using Annex AA of IEC 61010-2-020:2006 (2<sup>nd</sup> Ed.). The sealed buckets were shown to contain a spill.

Report Written By

Name: Ms Anna Mov

Title: Biosafety Scientist

Report Authorised By

Name: Mrs Sara Speight

Title: Senior Biosafety Scientist

Please be aware that the use of the Royal Coat of Arms is highly restricted and cannot be copied. Please do not put the PHE logo on your website or use our name to endorse your products. Any reference to PHE needs to be approved by us before it can be used.

<sup>#</sup> Part no. will form part of catalogue number 5820 748.001

<sup>\*</sup> Part no. will form part of catalogue number 5895 128.009; 5895 124.003; 5895 125.000



# **Certificate of Containment Testing**

Containment Testing of Rotor S-4x750 (5895 120.105-00) with Plate Buckets (5895 124.119-00\*) and Caps (5895 104.304-00\*) in an Eppendorf Bench Top Centrifuge

Report No. 14/043 B

Report Prepared For: Eppendorf AG, Hamburg, Germany

**Issue Date:** 17<sup>th</sup> February 2015

## **Test Summary**

Rotor S-4x750 (5895 120.105-00) with Plate Buckets (5895 124.119-00\*) and Caps (5895 104.304-00\*) was containment tested in an Eppendorf bench top centrifuge, using Annex AA of IEC 61010-2-020:2006 (2<sup>nd</sup> Ed.). The sealed buckets were shown to contain a spill.

Report Written By

Name: Ms Anna Moy

Anna May

Title: Biosafety Scientist

Report Authorised By

Name: Mrs Sara Speight

Title: Senior Biosafety Scientist

<sup>\*</sup> Part no. will form part of catalogue number 5895 128.009; 5895 124.003; 5895 125.000 # Part no. will form part of catalogue number 5895 111.009



# **Certificate of Containment Testing**

# Containment Testing of Rotor FA-6x50 (5895 150.101-00\*) in an Eppendorf Bench Top Centrifuge

Report No. 14/029 A

Report Prepared For: Eppendorf AG, Hamburg, Germany

Issue Date: 17<sup>th</sup> February 2015

## **Test Summary**

Rotor FA-6x50 (5895 150.101-00\*) was containment tested in an Eppendorf bench top centrifuge, using Annex AA of IEC 61010-2-020:2006 (2<sup>nd</sup> Ed.). The sealed rotor was shown to contain a spill.

Report Written By

Anna M

Name: Ms Anna Mov

Title: Biosafety Scientist

Report Authorised By

Name: Mrs Sara Speight

Title: Senior Biosafety Scientist



# **Certificate of Containment Testing**

# Containment Testing of Rotor FA-20x5 (5895 130.100-00\*) in an Eppendorf Bench Top Centrifuge

Report No. 14/029 B

Report Prepared For: Eppendorf AG, Hamburg, Germany

**Issue Date:** 17<sup>th</sup> February 2015

## **Test Summary**

Rotor FA-20x5 (5895 130.100-00\*) was containment tested in an Eppendorf bench top centrifuge, using Annex AA of IEC 61010-2-020:2006 (2<sup>nd</sup> Ed.). The sealed rotor was shown to contain a spill.

Report Written By

Name: Ms Anna Moy

Title: Biosafety Scientist

Anna Ma

Report Authorised By

Name: Mrs Sara Speight

Title: Senior Biosafety Scientist



# **Certificate of Containment Testing**

# Containment Testing of Rotor FA-48x2 (5895 135.102-00\*) in an Eppendorf Bench Top Centrifuge

Report No. 14/029 C

Report Prepared For: Eppendorf AG, Hamburg, Germany

**Issue Date:** 17<sup>th</sup> February 2015

## **Test Summary**

Rotor FA-48x2 (5895 135.102-00\*) was containment tested in an Eppendorf bench top centrifuge, using Annex AA of IEC 61010-2-020:2006 (2<sup>nd</sup> Ed.). The sealed rotor was shown to contain a spill.

Report Written By

Name: Ms Anna Moy

Title: Biosafety Scientist

Report Authorised By

Name: Mrs Sara Speight

Title: Senior Biosafety Scientist



# **Certificate of Containment Testing**

# Containment Testing of Rotor FA-30x2 (5895 155.103-00\*) in an Eppendorf Bench Top Centrifuge

Report No. 14/029 D

Report Prepared For: Eppendorf AG, Hamburg, Germany

**Issue Date:** 17<sup>th</sup> February 2015

## **Test Summary**

Rotor FA-30x2 (5895 155.103-00\*) was containment tested in an Eppendorf bench top centrifuge, using Annex AA of IEC 61010-2-020:2006 (2<sup>nd</sup> Ed.). The sealed rotor was shown to contain a spill.

Report Written By

Name: Ms Anna Moy

Anna Ma

Title: Biosafety Scientist

Report Authorised By

Name: Mrs Sara Speight

Title: Senior Biosafety Scientist



Public Health England National Infection Service Porton Down Salisbury Wiltshire SP4 OJG

# **Certificate of Containment Testing**

Containment Testing of Rotor FA-6x250 (5895 175.104-00\*) with Lid (5895 175.309-00<sup>#</sup>) in an Eppendorf Bench Top Centrifuge

Report No. 18/030 B

Report Prepared For: Eppendorf AG, Hamburg, Germany

Issue Date: 24 January 2019

## **Test Summary**

Rotor FA-6x250 was containment tested in an Eppendorf bench top centrifuge, using Annex AA of IEC 61010-2-020:2016 (3<sup>rd</sup> Ed.). The sealed rotor was designed to prevent any spill reaching the rotor lid and therefore preventing migration of spores across the seal.

**Report Written By** 

Name: Ms Anna Moy

Anna May

Title: Biosafety Scientist

Report Authorised By

Name: Mrs Sara Speight

Title: Senior Biosafety Scientist

<sup>\*</sup> Part no. will form part of catalogue number 5895 175.007 # Part no. will form part of catalogue number 5895 176.003



# **Certificate of Containment Testing**

Containment Testing of Rotor S-4x400 (5895 180.108-00) with Roundbucket (5895 182.119-00\*) and Caps (5910 700.105-00<sup>#</sup>) in an Eppendorf Bench Top Centrifuge

Report No. 17/006 A

Report Prepared For: Eppendorf AG, Hamburg, Germany

Issue Date: 28 June 2017

## **Test Summary**

Rotor S-4x400 (5895 180.108-00) with Roundbucket (5895 182.119-00\*) and Caps (5910 700.105-00\*) was containment tested in an Eppendorf bench top centrifuge, using Annex AA of IEC 61010-2-020:2016 (3<sup>rd</sup> Ed.). The sealed buckets were shown to contain a spill.

Report Written By

**Report Authorised By** 

Name: Ms Anna Mov

mua W

Title: Biosafety Scientist

Name: Mrs Sara Speight

Title: Senior Biosafety Scientist

<sup>\*</sup> Part no. will form part of catalogue number 5895 180.000; 5895 182.003; 5895 183.000

<sup>\*</sup>Part no. will form part of catalogue number 5910 700.008



## **Certificate of Containment Testing**

Containment Testing of Rotor S-4x500 (5895 170.102-00) with Rectangle Buckets (5810 719.119-02\*) and Caps (5810 724.104-00\*) in an Eppendorf Bench Top Centrifuge

Report No. 17/006 B

Report Prepared For: Eppendorf AG, Hamburg, Germany

**Issue Date:** 18 September 2017

## **Test Summary**

Rotor S-4x500 (5895 170.102-00) with Rectangle Buckets (5810 719.119-02\*) and Caps (5810 724.104-00\*) was containment tested in an Eppendorf bench top centrifuge, using Annex AA of IEC 61010-2-020:2016 (3<sup>rd</sup> Ed.). The sealed buckets were shown to contain a spill.

Report Written By

Anna V

Report Authorised By

Name: Ms Anna Mov

Title: Biosafety Scientist

Name: Mrs Sara Speight

Title: Senior Biosafety Scientist

Part no. will form part of catalogue number 5895 170.005; 5810 730.007

<sup>\*</sup> Part no. will form part of catalogue number 5810 742.007



## **Certificate of Containment Testing**

**Containment Testing of Rotor** S-4xuniversal (5895 200.109-00) with Universal Buckets (5895 202.101-00\*) and Caps (5910 750.120-00<sup>#</sup>) in an Eppendorf **Bench Top Centrifuge** 

Report No. 17/006 C

Report Prepared For: Eppendorf AG, Hamburg, Germany

Issue Date: 18 September 2017

## **Test Summary**

Rotor S-4xuniversal (5895 200.109-00) with Universal Buckets (5895 202.101-00\*) and Caps (5910 750.120-00#) was containment tested in an Eppendorf bench top centrifuge, using Annex AA of IEC 61010-2-020:2016 (3<sup>rd</sup> Ed.). The sealed buckets were shown to contain a spill.

Report Written By

Report Authorised By

Name: Ms Anna Moy

Title: Biosafety Scientist

Name: Mrs Sara Speight

Title: Senior Biosafety Scientist

<sup>\*</sup> Part no. will form part of catalogue number 5895 200.001; 5895 202.004; 5895 203.000

<sup>\*</sup>Part no. will form part of catalogue number 5910 750.005



## **Evaluate Your Manual**

Give us your feedback. www.eppendorf.com/manualfeedback